Introduction M610-100 1-1

Introduction 1

1.1 Introduction to this Service Manual

The T610 MDT Service Manual is provided for use by personnel who are required to service and maintain the MDT. This manual consists of seven chapters as follows:

This chapter Introduces the T610 MDT and provides relevant technical

and performance data.

Chapter 2 **Health and Safety Information**

> States the hazards associated with service and maintenance of the MDT, and the means by which such hazards

can be avoided.

Chapter 3 **Circuit Operation**

Provides a functional description of the MDT's electronic

circuitry.

Chapter 4 Servicing

Provides instructions for disassembling, servicing and

assembling the MDT.

Functional Tests Chapter 5

Describes the on-board test facilities that can be used to

check that the MDT is functioning correctly.

Chapter 6 Fault Finding

A series of charts are provided to assist during fault find-

ing and rectification.

Chapter 7 **PCB Information**

Provides a circuit diagram, PCB layouts, grid reference

index and parts list for the MDT's Main printed circuit board (PCB).

If further information is required about the T610 MDT or this Manual, it can be obtained from Tait Electronics Ltd. or accredited agents. When requesting this information, please quote the equipment type number (e.g. T610-110) and serial number. In the case of the Service Manual quote the Tait Internal Part Number (IPN), e.g. M610-100-100, and for circuit diagrams quote the Title, IPN and Issue.

Copyright TEL 15/6/95 1-2 Introduction M610-100

1.2 Introduction to the T610 MDT

The T610 Mobile Data Terminal (MDT) is part of the Tait *inform* suite of products for computer-assisted voice and data despatch. The T610 MDT operates in conjunction with a data-capable T2000 mobile radio, combining all the features of the T2000 with text massaging capability.




Figure 1.1 T610 Mobile Data Terminal

Most of the functions of the MDT are microprocessor controlled. The system software is stored in Flash read-only memory (ROM). The operating parameters are programmable and stored in non-volatile random access memory (RAM). Programming is achieved using a personal computer (PC) via the MDT's EIA 232 data communications port.

15/6/95 Copyright TEL

M610-100 **Introduction 1-3**

1.3 Specifications

The performance figures stated herein are typical values, unless otherwise indicated, for equipment operating at standard room temperature.

The test methods used to obtain the performance data are, where applicable, those described in the European specification ETS 300-113. Details of test methods and the conditions which apply for type approval testing in all countries can be obtained from Tait Electronics Limited.

1.3.1 Mechanical Specifications

Construction .. High temperature plastic

Dimensions (w x h x d) 190 mm x 80 mm x 50 mm

(7.5" x 3.1" x 2")

Weight .. 570 g (1 lb 4 oz)

Operating temperature

Internal ... -10° C to $+60^{\circ}$ C Surface (sunshield fitted) ... -10° C to $+110^{\circ}$ C

Ambient storage temperature .. -20°C to +60°C

LCD screen display area .. 127 mm x 34 mm (5" x 1.3")

240 pixels x 64 pixels

External connectors .. 15-pin, D-range (female)

Keypad .. eight, multifunctional softkeys and

power on/off

Copyright TEL 15/6/95

1-4 *Introduction* M610-100

1.3.2 Electrical Specifications

Operating voltage ... 10.8 V to 16 V (nominal 13.8 V)

Current consumption

Backlighting on ... 400 mA (maximum), 300 mA (nominal) Backlighting off ... 100 mA (maximum), 50 mA (nominal)

Audible indicator ... Piezo, user adjustable volume

Memory

Flash ROM .. 128 KB Battery-backed static RAM .. 128 KB

Battery backup ... coin-type lithium, 3 V, 500 mAh

Radio interface

Electrical .. EIA 232

Communication protocol .. UADG MAP27 version 1.3

Communication speed .. 1200/9600 bps

Programming interface

Electrical .. EIA 232 Communication speed .. 4800 bps Software .. Tait PGM610

1.3.3 Miscellaneous Specifications

Messaging

Status messages .. up to 30 programmable strings; maxi-

mum 20 alphanumeric characters

Storage of received messages ... programmable, between 1 and 20

END OF CHAPTER 1

15/6/95 Copyright TEL