

6.2 T885 Receiver PCB

This section contains the following information.

IPN	Section	Page
220-01595-02	Parts List	6.2.3
	Mechanical & Miscellaneous Parts	6.2.10
	Grid Reference Index	6.2.11
	PCB Layout - Top Side	6.2.15
	PCB Layout - Bottom Side	6.2.16
	Receiver Overview Diagram	6.2.17
	Audio Processor Circuit Diagram	6.2.18
	IF Section Circuit Diagram	6.2.19
	Front End Circuit Diagram	6.2.20
	VCO Circuit Diagram	6.2.21
	Regulators Circuit Diagram	6.2.22
	Synthesiser Circuit Diagram	6.2.23
	Microcontroller Circuit Diagram	6.2.24
	Harmonic Filter Circuit Diagram	6.2.25

T885 Parts List (IPN 220-01595-02)

How To Use This Parts List

The components listed in this parts list are divided into two main types: those with a circuit reference (e.g. C2, D1, R121, etc.) and those without (miscellaneous and mechanical).

Those with a circuit reference are grouped in alphabetical order and then in numerical order within each group. Each component entry comprises three or four columns: the circuit reference, variant (if applicable), IPN and description. A number in the variant column indicates that this is a variant component which is fitted only to the product type listed. Static sensitive devices are indicated by an (S) at the start of the description column.

The miscellaneous and mechanical section lists the variant and common parts in IPN order. Where possible, a number in the legend column indicates their position in the mechanical assembly drawing.

The Parts List Amendments box below lists component changes that took place after the parts list and diagrams in this section were compiled. These changes (e.g. value changes, added/deleted components, etc.) are listed by circuit reference in alphanumeric order and supersede the information given in the parts list or diagrams. Components without circuit references are listed in IPN order.

Parts List Amendments

There were no amendments to the parts list at the time of publication.

Parts List Amendments - Continued

This page is provided for entering future amendments to the parts list.

Ref	Var	IPN	Description	Ref	Var	IPN	Description
C201		014-08100-00	CAP TANT CHIP 10M 16VW +20%	C348		015-25470-08	CAP CER 0805 47N 10% X7R 50V
C203		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C349		015-25470-08	CAP CER 0805 47N 10% X7R 50V
C205		015-24470-08	CAP CER 0805 4N7 10% X7R 50V	C350		015-22100-01	CAP CER 0805 10P+-1/2P NPO 50V
C207		014-07100-02	CAP TANT CHIP 1U0 3.2 X 1.6MM	C351		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C209		016-08470-03	CAP SMD ELEC 47mF 20% 25v 8.3m	C352		015-24100-08	CAP CER 0805 1N 10% X7R 50V
C210		015-24100-08	CAP CER 0805 1N 10% X7R 50V	C353		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C211		015-24470-08	CAP CER 0805 4N7 10% X7R 50V	C354		015-22560-01	CAP CER 0805 56P 5% NPO 50V
C212		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C355		015-22560-01	CAP CER 0805 56P 5% NPO 50V
C213		015-25470-08	CAP CER 0805 47N 10% X7R 50V	C356		015-24470-08	CAP CER 0805 4N7 10% X7R 50V
C215		015-21220-01	CAP CER 0805 2P2+-0.25 NPO 50V	C357		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C217		015-22470-01	CAP CER 0805 47P 5% NPO 50V	C358		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C219		015-24470-08	CAP CER 0805 4N7 10% X7R 50V	C359		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C221		015-24100-08	CAP CER 0805 1N 10% X7R 50V	C360		015-23120-01	CAP CER 0805 120P 5% NPO 50V
C222		014-08100-00	CAP TANT CHIP 10M 16VW +20%	C361		015-22560-01	CAP CER 0805 56P 5% NPO 50V
C223		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C362		015-22560-01	CAP CER 0805 56P 5% NPO 50V
C225		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C364		015-25470-08	CAP CER 0805 47N 10% X7R 50V
C227		015-23100-01	CAP CER 0805 100P 5% NPO 50V	C365		015-25470-08	CAP CER 0805 47N 10% X7R 50V
C229		014-08100-00	CAP TANT CHIP 10M 16VW +20%	C366		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C231		014-08100-00	CAP TANT CHIP 10M 16VW +20%	C367		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C233		014-08100-00	CAP TANT CHIP 10M 16VW +20%	C368		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C235		015-24100-08	CAP CER 0805 1N 10% X7R 50V	C369		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C237		015-24100-08	CAP CER 0805 1N 10% X7R 50V	C371		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C238		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C385		014-08100-00	CAP TANT CHIP 10M 16VW +20%
C239		016-09100-05	CAP SMD ELECT 100U 25V 20%	C386		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C240A		015-24100-08	CAP CER 0805 1N 10% X7R 50V	C387		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C240B		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C389		014-08100-00	CAP TANT CHIP 10M 16VW +20%
C240C		016-09470-01	LJCAP ELECT 470U 20% SMD	C390		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C249		016-09470-01	LJCAP ELECT 470U 20% SMD	C400		015-22180-05	CAP 0805 18P 1% 200V
C251		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C401		015-25150-08	CAP CER 0805 15N 10% X7R 50V
C253		016-09100-05	CAP SMD ELECT 100U 25V 20%	C402		015-22180-05	CAP 0805 18P 1% 200V
C255		015-24100-08	CAP CER 0805 1N 10% X7R 50V	C403		015-22180-05	CAP 0805 18P 1% 200V
C257		015-24100-08	CAP CER 0805 1N 10% X7R 50V	C404		015-22180-05	CAP 0805 18P 1% 200V
C259		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C407		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C260A		015-24100-08	CAP CER 0805 1N 10% X7R 50V	C408		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C260B		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C409		015-22180-05	CAP 0805 18P 1% 200V
C260C		016-09470-01	LJCAP ELECT 470U 20% SMD	C410		015-25150-08	CAP CER 0805 15N 10% X7R 50V
C261		016-09100-05	CAP SMD ELECT 100U 25V 20%	C411		015-22180-05	CAP 0805 18P 1% 200V
C262		016-09100-05	CAP SMD ELECT 100U 25V 20%	C414		015-22180-05	CAP 0805 18P 1% 200V
C264		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C415		015-22180-05	CAP 0805 18P 1% 200V
C266		016-07470-06	CAP SMD ELECT BI-P 4U7 50V 20%	C417		015-21330-05	CAP CER 0805 3P3+-0.1PF 200V
C268		016-07470-06	CAP SMD ELECT BI-P 4U7 50V 20%	C418		015-22390-05	CAP 0805 39P 1% 200V
C270		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C422		015-22390-05	CAP 0805 39P 1% 200V
C272		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C500		015-22180-05	CAP 0805 18P 1% 200V
C273		014-08100-00	CAP TANT CHIP 10M 16VW +20%	C501		014-08220-01	(LJ)CAP TANT 22UF10V276MSER
C274		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C502		014-08220-01	(LJ)CAP TANT 22UF10V276MSER
C276		015-25470-08	CAP CER 0805 47N 10% X7R 50V	C503		015-24100-08	CAP CER 0805 1N 10% X7R 50V
C278		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C504		015-22180-05	CAP 0805 18P 1% 200V
C280		015-25470-08	CAP CER 0805 47N 10% X7R 50V	C505		015-22180-05	CAP 0805 18P 1% 200V
C286		015-24470-08	CAP CER 0805 4N7 10% X7R 50V	C506		015-22180-05	CAP 0805 18P 1% 200V
C300		015-23100-01	CAP CER 0805 100P 5% NPO 50V	C507		015-22180-05	CAP 0805 18P 1% 200V
C302		015-24470-08	CAP CER 0805 4N7 10% X7R 50V	C508		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C303		015-22150-01	CAP CER 0805 15P 5% NPO 50V	C509		015-24100-08	CAP CER 0805 1N 10% X7R 50V
C304		015-24470-08	CAP CER 0805 4N7 10% X7R 50V	C510		015-22180-05	CAP 0805 18P 1% 200V
C307		014-08100-00	CAP TANT CHIP 10M 16VW +20%	C516		014-08220-01	(LJ)CAP TANT 22UF10V276MSER
C308		015-24100-08	CAP CER 0805 1N 10% X7R 50V	&C517	10	015-22180-05	CAP 0805 18P 1% 200V
&C309	10	015-22220-01	CAP CER 0805 22P 5% NPO 50V	&C517	25	015-22180-05	CAP 0805 18P 1% 200V
&C309	25	015-22270-01	CAP CER 0805 27P 5% NPO 50V	&C517	30	015-22180-05	CAP 0805 18P 1% 200V
&C309	30	015-22220-01	CAP CER 0805 22P 5% NPO 50V	C518		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C310		015-25100-08	CAP CER 0805 10N 10% X7R 50V	&C519	10	015-22390-05	CAP 0805 39P 1% 200V
&C311	10	015-22100-01	CAP CER 0805 10P+-1/2P NPO 50V	&C519	25	015-22390-05	CAP 0805 39P 1% 200V
&C311	25	015-21820-02	LJCAP 0805 8P2 15 NPO 50V	&C519	30	015-22330-05	CAP CER 0805 33P+-0.1PF 200V
&C311	30	015-22100-01	CAP CER 0805 10P+-1/2P NPO 50V	C520		015-22180-05	CAP 0805 18P 1% 200V
&C314	10	015-21820-02	LJCAP 0805 8P2 15 NPO 50V	&C521	10	015-23330-08	CAP CER 0805 330P 10% X7R 50V
&C314	25	015-22180-05	CAP 0805 18P 1% 200V	&C521	25	015-23330-08	CAP CER 0805 330P 10% X7R 50V
&C314	30	015-21820-02	LJCAP 0805 8P2 15 NPO 50V	&C521	30	015-23330-08	CAP CER 0805 330P 10% X7R 50V
&C315	10	015-21820-02	LJCAP 0805 8P2 15 NPO 50V	&C522	10	015-21150-05	CAP CER 0805 CHIP 1P5+-0.1PF 2
&C315	25	015-21560-01	CAP CER 0805 5P6+-0.25 NPO 50V	&C522	25	015-21150-05	CAP CER 0805 CHIP 1P5+-0.1PF 2
&C315	30	015-21820-02	LJCAP 0805 8P2 15 NPO 50V	&C522	30	015-21150-05	CAP CER 0805 CHIP 1P5+-0.1PF 2
C316		015-25100-08	CAP CER 0805 10N 10% X7R 50V	&C524	10	015-21120-05	CAP CER 0805 CHIP 1P2 +0.1PF 2
C317		015-22470-01	CAP CER 0805 47P 5% NPO 50V	&C524	25	015-21120-05	CAP CER 0805 CHIP 1P2 +0.1PF 2
&C318	10	015-21560-01	CAP CER 0805 5P6+-0.25 NPO 50V	&C524	30	015-21100-05	CAP CER 0805 1P0 +0.1PF 200V
&C318	25	015-21680-01	CAP CER 0805 6P8+-0.25 NPO 50V	&C525	10	015-21100-05	CAP CER 0805 1P0 +0.1PF 200V
&C318	30	015-21560-01	CAP CER 0805 5P6+-0.25 NPO 50V	&C525	25	015-21100-05	CAP CER 0805 1P0 +0.1PF 200V
C321		015-25100-08	CAP CER 0805 10N 10% X7R 50V	&C525	30	015-20075-05	CAP CER 0805 CHIP OP75+-0.1PF
C322		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C531		015-22180-05	CAP 0805 18P 1% 200V
C324		015-23100-01	CAP CER 0805 100P 5% NPO 50V	&C533	10	015-21180-05	CAP CER 0805 1P8 +-0.1 200V
C325		015-25100-08	CAP CER 0805 10N 10% X7R 50V	&C533	25	015-21180-05	CAP CER 0805 1P8 +-0.1 200V
C328		015-25100-08	CAP CER 0805 10N 10% X7R 50V	&C533	30	015-21150-05	CAP CER 0805 CHIP 1P5+-0.1PF 2
&C329	25	015-21330-05	CAP CER 0805 3P3+-0.1PF 200V	C536		015-22180-05	CAP 0805 18P 1% 200V
&C330	10	015-25100-08	CAP CER 0805 10N 10% X7R 50V	C537		015-26100-08	CAP CER 0805 100N 10% X7R 50V
&C330	25	015-22100-01	CAP CER 0805 10P+-1/2P NPO 50V	C540		015-22180-05	CAP 0805 18P 1% 200V
&C330	30	015-25100-08	CAP CER 0805 10N 10% X7R 50V	C541		015-22180-05	CAP 0805 18P 1% 200V
&C331	10	015-21680-01	CAP CER 0805 6P8+-0.25 NPO 50V	C542		014-08220-01	(LJ)CAP TANT 22UF10V276MSER
&C331	25	015-21330-05	CAP CER 0805 3P3+-0.1PF 200V	C543		015-22180-05	CAP 0805 18P 1% 200V
&C331	30	015-21680-01	CAP CER 0805 6P8+-0.25 NPO 50V	C544		015-22180-05	CAP 0805 18P 1% 200V
&C332	25	015-21270-05	CAP CER 0805 CHIP 2P7 +0.1PF 2	C545		015-22180-05	CAP 0805 18P 1% 200V
&C335	25	015-21330-05	CAP CER 0805 3P3+-0.1PF 200V	C548		015-22180-05	CAP 0805 18P 1% 200V
C336		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C549		015-22180-05	CAP 0805 18P 1% 200V
C337		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C555		015-22180-05	CAP 0805 18P 1% 200V
C338		015-22270-01	CAP CER 0805 27P 5% NPO 50V	C556		015-22180-05	CAP 0805 18P 1% 200V
C339		015-22220-01	CAP CER 0805 22P 5% NPO 50V	C557		015-22180-05	CAP 0805 18P 1% 200V
C340		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C558		015-22180-05	CAP 0805 18P 1% 200V
C341		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C559		014-07470-00	CAP 4U7 SMD 'B'CASE 16V +-010%
C342		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C560		015-22180-05	CAP 0805 18P 1% 200V
C343		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C561		015-22180-05	CAP 0805 18P 1% 200V
C345		014-07470-00	CAP 4U7 SMD 'B'CASE 16V +-010%	C562		015-22180-05	CAP 0805 18P 1% 200V
C346		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C563		015-26100-08	CAP CER 0805 100N 10% X7R 50V
C347		015-25470-08	CAP CER 0805 47N 10% X7R 50V	C564		015-22180-05	CAP 0805 18P 1% 200V

Ref	Var	IPN	Description	Ref	Var	IPN	Description
C569		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C818		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C570		015-22180-05	CAP 0805 18P 1% 200V	C819		015-22330-01	CAP CER 0805 33P 5% NPO 50V
C571		015-22180-05	CAP 0805 18P 1% 200V	C820		015-23220-01	CAP CER 0805 220P 5% NPO 50V
C572		015-22180-05	CAP 0805 18P 1% 200V	C822		015-25220-08	CAP CER 0805 22N 10% X7R 50V
C573		014-07470-00	CAP 4U7 SMD 'B'CASE 16V +-010%	C824		015-25470-08	CAP CER 0805 47N 10% X7R 50V
C574		015-22180-05	CAP 0805 18P 1% 200V	C826		015-05100-07	CAP 1206 CHIP NPO 10nF 25V
C575		015-22180-05	CAP 0805 18P 1% 200V	C828		015-05100-07	CAP 1206 CHIP NPO 10nF 25V
C576		015-22180-05	CAP 0805 18P 1% 200V	C830		015-25470-08	CAP CER 0805 47N 10% X7R 50V
C577		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C832		014-07100-02	CAP TANT CHIP 1U0 3.2 X 1.6MM
C578		015-21270-05	CAP CER 0805 CHIP 2P7 +-0.1PF 2	C833		015-25220-08	CAP CER 0805 22N 10% X7R 50V
C579		015-21330-05	CAP CER 0805 3P3+-0.1PF 200V	C834		015-25100-08	CAP CER 0805 10N 10% X7R 50V
C585		015-22180-05	CAP 0805 18P 1% 200V	C836		015-05100-07	CAP 1206 CHIP NPO 10nF 25V
C586		015-22180-05	CAP 0805 18P 1% 200V	C837		015-05100-07	CAP 1206 CHIP NPO 10nF 25V
C587		015-21470-05	CAP CER 0805 4P7+-0.1PF 200V	C838		015-05100-07	CAP 1206 CHIP NPO 10nF 25V
C588		015-22180-05	CAP 0805 18P 1% 200V	C840		015-25470-08	CAP CER 0805 47N 10% X7R 50V
C590		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C842		014-07100-02	CAP TANT CHIP 1U0 3.2 X 1.6MM
C591		015-22180-05	CAP 0805 18P 1% 200V	C844		014-07100-02	CAP TANT CHIP 1U0 3.2 X 1.6MM
C592		014-08220-01	(L)CAP TANT 22UF10V276MSER	C846		014-07100-02	CAP TANT CHIP 1U0 3.2 X 1.6MM
C593		015-22180-05	CAP 0805 18P 1% 200V	C848		014-07100-02	CAP TANT CHIP 1U0 3.2 X 1.6MM
C594		015-22180-05	CAP 0805 18P 1% 200V	C850		015-25470-08	CAP CER 0805 47N 10% X7R 50V
C595		015-22180-05	CAP 0805 18P 1% 200V	C873		015-25220-08	CAP CER 0805 22N 10% X7R 50V
C596		015-26100-08	CAP CER 0805 100N 10% X7R 50V	C876		014-09100-00	CAP TANT SMD 100U 16V 20%
C597		015-22180-05	CAP 0805 18P 1% 200V	C879		014-08100-00	CAP TANT CHIP 10M 16VW +-20%
C610A		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C900		015-21220-01	CAP CER 0805 2P2+-0.25 NPO 50V
C610B		014-09100-00	CAP TANT SMD 100U 16V 20%	C901		015-21390-01	CAP CER 0805 3P9+-0.25 NPO 50V
C611A		014-09100-00	CAP TANT SMD 100U 16V 20%	C902		015-21390-01	CAP CER 0805 3P9+-0.25 NPO 50V
C611B		015-25100-08	CAP CER 0805 10N 10% X7R 50V	C903		015-21220-01	CAP CER 0805 2P2+-0.25 NPO 50V
C623		015-22180-05	CAP 0805 18P 1% 200V	CV500		028-11500-00	CAP TRIM 0.6/4.5 P SAPPHERE
C625		020-09470-07	CAP ELEC RADL 470M 16V 20% 3.5				
C626		015-24470-08	CAP CER 0805 4N7 10% X7R 50V	%D111A		001-10015-50	DIODE SMD ZENER 1.5SMC22AT3
C628		015-24100-08	CAP CER 0805 1N 10% X7R 50V	D220		001-10000-56	S) DIODE SMD BAW56 D-SW SOT23
C630		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D230		001-10000-70	S) DIODE SMD BAV70 D-SW SOT23
C631A		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D240		001-10000-99	S) DIODE SMD BAV99 D-SW SOT23
C631B		014-08100-03	CAP TANT SMD 10U 35V 20%	D250		008-00014-79	S)LED 3MM RED WITH WIRE
C637		015-22180-05	CAP 0805 18P 1% 200V	D260		001-10084-33	S)DIODE ZENSMD BZX84C3V3 SOT23
C640		015-24100-08	CAP CER 0805 1N 10% X7R 50V	D270		001-10000-70	S) DIODE SMD BAV70 D-SW SOT23
C650		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D280		008-00014-80	S)LED 3MM GREEN WITH WIRE
C651		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D285		001-10011-73	DIODE SMD MRA4003T3 1A/300V SM
C658		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D289		001-10011-73	DIODE SMD MRA4003T3 1A/300V SM
C660		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D290		001-10011-73	DIODE SMD MRA4003T3 1A/300V SM
C665		014-08100-03	CAP TANT SMD 10U 35V 20%	D295		001-10011-73	DIODE SMD MRA4003T3 1A/300V SM
C670		014-07330-10	CAP TANT SMD 3U3 35V 10%	D330		001-10000-99	S) DIODE SMD BAV99 D-SW SOT23
C673		015-24470-08	CAP CER 0805 4N7 10% X7R 50V	D501		001-10005-35	S) DIODE SMD VCAP BB535 SOD323
C677		014-07100-02	CAP TANT CHIP 1U0 3.2 X 1.6MM	D502		001-10005-35	S) DIODE SMD VCAP BB535 SOD323
C681		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D504		001-10005-35	S) DIODE SMD VCAP BB535 SOD323
C684		014-08100-03	CAP TANT SMD 10U 35V 20%	D505		001-10005-35	S) DIODE SMD VCAP BB535 SOD323
C687		015-22180-05	CAP 0805 18P 1% 200V	D610		001-10000-99	S) DIODE SMD BAV99 D-SW SOT23
C690		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D640		001-10000-70	S) DIODE SMD BAV70 D-SW SOT23
C693		014-08100-03	CAP TANT SMD 10U 35V 20%	D645		001-10010-40	DIODE SMD ZENER 33V BZG03-C33
C700		015-26100-08	CAP CER 0805 100N 10% X7R 50V	D730A		001-10165-00	DIODE BAT165 SCHOTTKY SOD-323
C702		015-24100-08	CAP CER 0805 1N 10% X7R 50V	D740A		001-10165-00	DIODE BAT165 SCHOTTKY SOD-323
C703		015-24100-08	CAP CER 0805 1N 10% X7R 50V	D820A		001-10165-00	DIODE BAT165 SCHOTTKY SOD-323
C705		015-21820-02	L)CAP 0805 8P2 15 NPO 50V	D860		001-10000-70	S) DIODE SMD BAV70 D-SW SOT23
C707		015-22470-01	CAP CER 0805 47P 5% NPO 50V	D880		001-10000-70	S) DIODE SMD BAV70 D-SW SOT23
C708		015-22470-01	CAP CER 0805 47P 5% NPO 50V				
C709		015-22100-01	CAP CER 0805 10P+-1/2P NPO 50V	#H400	10	051-00564-00	COIL HELC RES 2.625T 1.2MMSF
C710A		014-07470-00	CAP 4U7 SMD 'B'CASE 16V +-010%	#H400	25	051-00565-00	COIL HELC RES 2.428T 1.2MMSF
C710B		015-26100-08	CAP CER 0805 100N 10% X7R 50V	#H400	30	051-00565-00	COIL HELC RES 2.428T 1.2MMSF
C710C		015-25100-08	CAP CER 0805 10N 10% X7R 50V	#H401	10	051-00564-00	COIL HELC RES 2.625T 1.2MMSF
C711		015-22220-01	CAP CER 0805 22P 5% NPO 50V	#H401	25	051-00565-00	COIL HELC RES 2.428T 1.2MMSF
C712		015-22220-01	CAP CER 0805 22P 5% NPO 50V	#H401	30	051-00565-00	COIL HELC RES 2.428T 1.2MMSF
C713		015-25100-08	CAP CER 0805 10N 10% X7R 50V	#H900	10	051-00564-00	COIL HELC RES 2.625T 1.2MMSF
C735		015-22470-01	CAP CER 0805 47P 5% NPO 50V	#H900	25	051-00565-00	COIL HELC RES 2.428T 1.2MMSF
C736		015-22470-01	CAP CER 0805 47P 5% NPO 50V				
C740A		015-24100-08	CAP CER 0805 1N 10% X7R 50V	IC210		002-10003-58	S) IC SMD LM358 DUAL O-AMP
C740B		015-25100-08	CAP CER 0805 10N 10% X7R 50V	IC240		002-00014-05	S) IC TDA7231 1.6W AF PWR
C741A		014-07470-00	CAP 4U7 SMD 'B'CASE 16V +-010%	IC260		002-00014-05	S) IC TDA7231 1.6W AF PWR
C741B		015-25100-08	CAP CER 0805 10N 10% X7R 50V	IC270		002-10003-58	S) IC SMD LM358 DUAL O-AMP
C742A		015-26100-08	CAP CER 0805 100N 10% X7R 50V	IC280		002-10003-58	S) IC SMD LM358 DUAL O-AMP
C742B		015-25100-08	CAP CER 0805 10N 10% X7R 50V	IC300		002-10337-20	S) IC MC3372D SMD IF DETECTOR
C743		015-22470-01	CAP CER 0805 47P 5% NPO 50V	IC330		002-10008-40	S)IC SMD TL084CD 4X O-AMP JFET
C745		015-22180-05	CAP 0805 18P 1% 200V	IC345		276-10010-14	FLTR CER SMD 455KHz E15KHz B/W
C750		014-08100-03	CAP TANT SMD 10U 35V 20%	IC351		002-10003-58	S) IC SMD LM358 DUAL O-AMP
C757		015-25100-08	CAP CER 0805 10N 10% X7R 50V	IC352		002-10003-58	S) IC SMD LM358 DUAL O-AMP
C759		015-25100-08	CAP CER 0805 10N 10% X7R 50V	IC360		002-10078-05	S) IC SMD 78L05 5V REG
C761		015-25100-08	CAP CER 0805 10N 10% X7R 50V	IC610		002-10078-05	S) IC SMD 78L05 5V REG
C762		014-08220-01	(L)CAP TANT 22UF10V276MSER	IC630		002-12523-17	(S)IC LM317L REG TO-252 0.5A
C764		015-25100-08	CAP CER 0805 10N 10% X7R 50V	IC640		002-10003-58	S) IC SMD LM358 DUAL O-AMP
C765		014-07470-00	CAP 4U7 SMD 'B'CASE 16V +-010%	IC650		002-10012-32	SMD DS1232LPS-2 LP RESET&W-DOG
C767		015-24100-08	CAP CER 0805 1N 10% X7R 50V	=IC700		539-00010-55	TCXO 12.8M 1PPM-20+70/2PPM -30
C769		015-24100-08	CAP CER 0805 1N 10% X7R 50V	IC710		002-74900-04	S) IC SMD 74HC04D 6X INV BUFFD
C770		014-08220-01	(L)CAP TANT 22UF10V276MSER	IC740		002-14519-10	S) IC MC145191F SMD SYNTH
C772		014-08220-01	(L)CAP TANT 22UF10V276MSER	IC750		002-10330-78	S) IC MC33078D 2X AMP LO NOISE
C774		013-06100-10	CAP SMD PPS 100N 100V 10%	IC820		002-12416-00	S)IC SMD AT24C16N-10SC EEPROM
C776		015-24680-08	CAP CER 0805 6N8 10% X7R 50V	IC830		002-10003-24	S) IC SMD 324 4X O-AMP SO14
C780		015-22180-05	CAP 0805 18P 1% 200V	IC840		002-10040-53	S)MC14053B SMD BREAK B4 MAKE
C782		015-22180-05	CAP 0805 18P 1% 200V	IC850		002-10003-24	S) IC SMD 324 4X O-AMP SO14
C784		015-22180-05	CAP 0805 18P 1% 200V	L230		057-10100-60	IND SHLD 100UH SMD 600MA
C786		015-26100-08	CAP CER 0805 100N 10% X7R 50V	L300		050-00016-22	COIL TAIT NO 622 20-120M
C788		015-22180-05	CAP 0805 18P 1% 200V	L301		050-00016-22	COIL TAIT NO 622 20-120M
C790		015-21330-05	CAP CER 0805 3P3+-0.1PF 200V	L302		059-16470-10	(L)IND FXD 1008CS 470NH 5%
C792		015-21560-01	CAP CER 0805 5P6+-0.25 NPO 50V	&L303	10	056-14150-02	(L) IND SMD 1.5UH SIMID02
C810		015-25100-08	CAP CER 0805 10N 10% X7R 50V	&L303	25	056-10820-02	(L) IND SMD 820NH SIMID02
C812		015-23100-01	CAP CER 0805 100P 5% NPO 50V	&L303	30	056-14150-02	(L) IND SMD 1.5UH SIMID02
C813		015-24100-08	CAP CER 0805 1N 10% X7R 50V	&L304	25	056-10820-02	(L) IND SMD 820NH SIMID02
C814		015-22180-05	CAP 0805 18P 1% 200V				
C815		015-05100-07	CAP 1206 CHIP NPO 10nF 25V				
C816		015-25100-08	CAP CER 0805 10N 10% X7R 50V				

Ref	Var	IPN	Description	Ref	Var	IPN	Description
&L307	10	056-14330-02	(L) IND SMD 3.3UH SIMID02	&R209	25	036-15180-00	RES M/F 0805 18K 5%
&L307	25	056-14150-02	(L) IND SMD 1.5UH SIMID02	&R209	30	036-15220-00	RES M/F 0805 22K 5%
&L307	30	056-14330-02	(L) IND SMD 3.3UH SIMID02	R210		036-15150-00	RES M/F 0805 15K 5%
L308		056-10820-00	IND FXD SMD 820NH 3.2*2.5*1.6	R211		036-15390-10	RES M/F 0805 39K 1%
L345		050-15119-75	COIL SMD 455KHz IF 5119-T075	R213		036-14270-10	RES M/F 0805 2K7 1%
L400		056-10330-02	(L) IND SMD 330NH SIMID02	R215		036-15150-00	RES M/F 0805 15K 5%
L404		056-10330-02	(L) IND SMD 330NH SIMID02	R218		036-14390-10	RES M/F 0805 3K9 1%
L410		056-10330-02	(L) IND SMD 330NH SIMID02	&R219	10	036-15100-10	RES M/F 0805 10K 1%
L414		056-10330-02	(L) IND SMD 330NH SIMID02	&R219	25	036-14820-10	RES M/F 0805 8K2 1%
L500		065-10004-20	BEAD FE SMD CBD 4.6/3/3-4S2	&R219	30	036-15100-10	RES M/F 0805 10K 1%
L501		056-10100-02	(L) IND SMD 100NH SIMID02	R221		036-15470-10	RES M/F 0805 47K 1%
L502		056-10100-02	(L) IND SMD 100NH SIMID02	R222		036-16100-10	RES M/F 0805 100K 1%
L503		065-10004-20	BEAD FE SMD CBD 4.6/3/3-4S2	%R223		036-12100-10	RES M/F 0805 10E 1%
L504		056-10100-02	(L) IND SMD 100NH SIMID02	R224		036-14390-10	RES M/F 0805 3K9 1%
L505		065-10004-20	BEAD FE SMD CBD 4.6/3/3-4S2	R225		036-13470-00	RES M/F 0805 470E 5%
L540		056-10082-02	(L) IND SMD 82NH SIMID02	R227		036-14270-10	RES M/F 0805 2K7 1%
L541		056-10015-03	IND SMD 0805 15NH 20%	R229		036-14470-10	RES M/F 0805 4K7 1%
L543		056-10006-83	(LSH) IND SMD 0805 6.8NH 20%	R230		036-14470-10	RES M/F 0805 4K7 1%
L700		056-10006-83	(LSH) IND SMD 0805 6.8NH 20%	R232		036-15470-10	RES M/F 0805 47K 1%
L900		052-08120-15	COIL A/W 1.5T/2MM HOR 0.8MM	R233		036-14820-10	RES M/F 0805 8K2 1%
L901		052-08125-15	COIL A/W 1.5T/2.5MM HOR 0.8MM	R234		036-15470-10	RES M/F 0805 47K 1%
L902		052-08120-15	COIL A/W 1.5T/2MM HOR 0.8MM	R236		036-15470-10	RES M/F 0805 47K 1%
M400		002-10000-13	MIXER DBL BALANCE 5-1500MHZ	R238		036-11470-00	RES M/F 0805 4E7 10%
PL100		070-01001-00	D-RANGE 15 WAY COMPL T800	R239		036-14100-10	RES M/F 0805 1K 1%
PL200		240-10000-16	HEADER 4W PCB MTG SMD	R241		036-14100-10	RES M/F 0805 1K 1%
PL210		240-10000-16	HEADER 4W PCB MTG SMD	R242		036-13100-10	RES M/F 0805 100E 1%
PL220		240-10000-16	HEADER 4W PCB MTG SMD	R244		036-14680-10	RES M/F 0805 6K8 1%
PL230		240-10000-16	HEADER 4W PCB MTG SMD	R245		036-14100-10	RES M/F 0805 1K 1%
PL240		240-10000-16	HEADER 5W PCB MTG SMD	R247		036-14220-00	RES M/F 0805 2K2 5%
PL250		240-10000-16	HEADER 4W PCB MTG SMD	R249		036-15100-10	RES M/F 0805 10K 1%
PL260		240-10000-16	HEADER 4W PCB MTG SMD	R251		036-15390-10	RES M/F 0805 39K 1%
PL270		240-10000-16	HEADER 4W PCB MTG SMD	R252		036-14470-10	RES M/F 0805 4K7 1%
Q210		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R254		036-14820-10	RES M/F 0805 8K2 1%
Q220		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R255		036-15470-10	RES M/F 0805 47K 1%
Q230		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R256		036-14270-10	RES M/F 0805 2K7 1%
Q240		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R258		036-15470-10	RES M/F 0805 47K 1%
Q245		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R260		036-11470-00	RES M/F 0805 4E7 10%
Q250		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R261		036-13150-10	RES M/F 0805 150E 1%
Q255		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R262		036-14100-10	RES M/F 0805 1K 1%
Q260		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R264		036-15150-00	RES M/F 0805 15K 5%
Q270		000-10008-17	S) XSTR SMD BC817-25 NPN SOT23	R265		036-13100-10	RES M/F 0805 100E 1%
Q280		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R266		036-15470-10	RES M/F 0805 47K 1%
Q290		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R267		036-16390-00	RES M/F 0805 390K 5%
Q300		000-10003-10	S) XSTR SMD BFJ310 JFET UHF	R269		036-14220-00	RES M/F 0805 2K2 5%
Q301		000-10008-92	S) XSTR SMD BFS17 NPN SOT23	R271		036-16100-10	RES M/F 0805 100K 1%
Q302		000-10009-41	S) XSTR SMD BR941L SOT23	R272		036-15470-10	RES M/F 0805 47K 1%
Q346		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R273		036-15150-00	RES M/F 0805 15K 5%
Q400		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R274		036-13120-00	RES M/F 0805 120E 5%
Q401		000-10009-30	XSTR SMD BFR93A NPN SOT23	R275		036-13100-10	RES M/F 0805 100E 1%
Q402		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R276		036-13120-00	RES M/F 0805 120E 5%
Q403		000-10009-30	XSTR SMD BFR93A NPN SOT23	R277		036-14560-00	RES M/F 0805 5K6 5%
Q500		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R278		036-16220-00	RES M/F 0805 220K 5%
Q501		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R279		036-12270-00	RES M/F 0805 27E 5%
Q502		000-10008-07	S) XSTR SMD BC807 PNP SOT23 AF	R280		036-16100-10	RES M/F 0805 100K 1%
Q503		000-10008-07	S) XSTR SMD BC807 PNP SOT23 AF	R281		036-14470-10	RES M/F 0805 4K7 1%
Q504		000-10009-30	XSTR SMD BFR93A NPN SOT23	R282		036-16100-10	RES M/F 0805 100K 1%
Q540		000-10009-41	S) XSTR SMD BR941L SOT23	R284		036-13100-10	RES M/F 0805 100E 1%
Q541		000-10009-41	S) XSTR SMD BR941L SOT23	R285		036-15470-10	RES M/F 0805 47K 1%
Q542		000-10008-07	S) XSTR SMD BC807 PNP SOT23 AF	R287		036-15100-10	RES M/F 0805 10K 1%
Q543		002-10003-18	IC BGA318 MMIC AMPLIFIER	R288		036-14470-10	RES M/F 0805 4K7 1%
Q544		000-10008-07	S) XSTR SMD BC807 PNP SOT23 AF	R289		036-14680-10	RES M/F 0805 6K8 1%
Q545		000-10008-07	S) XSTR SMD BC807 PNP SOT23 AF	R290		036-14100-10	RES M/F 0805 1K 1%
Q546		000-10008-07	S) XSTR SMD BC807 PNP SOT23 AF	R292		036-14680-10	RES M/F 0805 6K8 1%
Q590		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R293		036-13560-10	RES M/F 0805 560E 1%
Q591		000-10008-07	S) XSTR SMD BC807 PNP SOT23 AF	R294		036-14100-10	RES M/F 0805 1K 1%
Q592		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R295		036-14680-10	RES M/F 0805 6K8 1%
Q620		000-00033-12	XSTR BD242 TO-220 PNP ISOLTD	R296		036-14120-00	RES M/F 0805 1K2 5%
Q630		000-10003-00	S) XSTR BSR30 PNP AF SOT-89	R297		030-52100-20	RES FILM AI 10E 5% 0.4W 4X1.6
Q660		000-10008-17	S) XSTR SMD BC817-25 NPN SOT23	R298		036-15470-10	RES M/F 0805 47K 1%
Q670		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R299		036-15470-10	RES M/F 0805 47K 1%
Q750		000-10008-07	S) XSTR SMD BC807 PNP SOT23 AF	R300		036-12820-00	RES M/F 0805 82E 5%
Q760		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R301		036-12100-10	RES M/F 0805 10E 1%
Q770		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R302		036-13100-10	RES M/F 0805 100E 1%
Q775		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R303		036-14270-10	RES M/F 0805 2K7 1%
Q780		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R304		036-14220-00	RES M/F 0805 2K2 5%
Q785		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R307		036-13100-10	RES M/F 0805 100E 1%
Q790		000-10003-12	S) XSTR SMD BFR31 N JFET SOT23	R308		036-15150-00	RES M/F 0805 15K 5%
Q795		000-10009-30	XSTR SMD BFR93A NPN SOT23	R309		036-15100-10	RES M/F 0805 10K 1%
Q810		000-10008-17	S) XSTR SMD BC817-25 NPN SOT23	R310		036-15100-10	RES M/F 0805 10K 1%
Q820		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	R311		036-13100-10	RES M/F 0805 100E 1%
Q840		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	&R312	10	036-12470-00	RES M/F 0805 47E 5%
Q850		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	&R312	25	036-12220-00	RES M/F 0805 22E 5%
Q860		000-10008-57	S) XSTR SMD BCW70 PNP SOT23 SS	&R312	30	036-12470-00	RES M/F 0805 47E 5%
Q870		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R314		036-14150-10	RES M/F 0805 1K5 1%
Q880		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R315		036-14330-10	RES M/F 0805 3K3 1%
Q890		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R316		036-14100-10	RES M/F 0805 1K 1%
Q895		000-10008-48	S) XSTR SMD BCW60 NPN SOT23 SS	R344		036-17100-10	RES M/F 0805 1M 1%
R160		036-12100-10	RES M/F 0805 10E 1%	R345		036-10000-00	RES M/F 0805 ZERO OHM
R201		036-14470-10	RES M/F 0805 4K7 1%	R347		036-12220-00	RES M/F 0805 22E 5%
R202		036-14470-10	RES M/F 0805 4K7 1%	&R349	10	036-15560-10	RES MF 0805 56K 1%
R204		036-15100-10	RES M/F 0805 10K 1%	&R349	25	036-16100-10	RES M/F 0805 100K 1%
R205		036-16220-00	RES M/F 0805 220K 5%	&R349	30	036-15560-10	RES MF 0805 56K 1%
R207		036-14820-10	RES M/F 0805 8K2 1%	R350		036-14150-10	RES M/F 0805 1K5 1%
&R209	10	036-15220-00	RES M/F 0805 22K 5%	R351		036-14100-10	RES M/F 0805 1K 1%
				R352		036-14220-00	RES M/F 0805 2K2 5%
				R353		036-15820-00	RES M/F 0805 82K 5%
				R354		036-16560-00	RES M/F 0805 560K 5%
				R355		036-15470-10	RES M/F 0805 47K 1%

Ref	Var	IPN	Description	Ref	Var	IPN	Description
R356		036-15220-00	RES M/F 0805 22K 5%	R563		036-16180-00	RES M/F 0805 180K 5%
R357		036-16120-10	RES M/F 0805 120K 1%	R564		036-12330-00	RES M/F 0805 33E 5%
R358		036-15100-10	RES M/F 0805 10K 1%	R571		036-11470-00	RES M/F 0805 4E7 10%
R359		036-15100-10	RES M/F 0805 10K 1%	R572		036-13820-00	RES M/F 0805 820E 5%
R362		036-15270-10	RES M/F 0805 27K 1%	R573		036-11470-00	RES M/F 0805 4E7 10%
R363		036-14820-10	RES M/F 0805 8K2 1%	R574		036-13820-00	RES M/F 0805 820E 5%
R364		036-14560-00	RES M/F 0805 5K6 5%	R575		036-14150-10	RES M/F 0805 1K5 1%
R365		036-15100-10	RES M/F 0805 10K 1%	R576		036-14680-10	RES M/F 0805 6K8 1%
R366		036-16220-00	RES M/F 0805 220K 5%	R578		036-12270-00	RES M/F 0805 27E 5%
R367		045-15100-00	RES NTC SMD 10K 5%	R579		036-14100-10	RES M/F 0805 1K 1%
R368		036-16390-00	RES M/F 0805 390K 5%	R580		036-10000-00	RES M/F 0805 ZERO OHM
R369		036-14560-00	RES M/F 0805 5K6 5%	R586		036-13470-00	RES M/F 0805 470E 5%
R370		036-14390-10	RES M/F 0805 3K9 1%	R590		036-14100-10	RES M/F 0805 1K 1%
R371		036-16220-00	RES M/F 0805 220K 5%	R591		036-15220-00	RES M/F 0805 22K 5%
R372		036-14100-10	RES M/F 0805 1K 1%	R592		036-14220-00	RES M/F 0805 2K2 5%
R373		036-16220-00	RES M/F 0805 220K 5%	R615		036-13100-10	RES M/F 0805 100E 1%
R374		036-15100-10	RES M/F 0805 10K 1%	R617		036-10000-00	RES M/F 0805 ZERO OHM
R375		036-15100-10	RES M/F 0805 10K 1%	R619		036-01100-10	RES 1 OHM 1 WATT 2512 CHIP
R376		036-15100-10	RES M/F 0805 10K 1%	R621		036-01100-10	RES 1 OHM 1 WATT 2512 CHIP
R377		036-16390-00	RES M/F 0805 390K 5%	R625		036-14100-10	RES M/F 0805 1K 1%
R378		036-14220-00	RES M/F 0805 2K2 5%	R629		036-03270-10	RES 270 OHM 1 WATT 2512 CHIP
R379		036-14820-10	RES M/F 0805 8K2 1%	R633		036-14680-10	RES M/F 0805 6K8 1%
R380		036-14100-10	RES M/F 0805 1K 1%	R636		036-12220-00	RES M/F 0805 22E 5%
R381		036-14560-00	RES M/F 0805 5K6 5%	R637		036-12220-00	RES M/F 0805 22E 5%
R382		036-14820-10	RES M/F 0805 8K2 1%	R640		036-12100-10	RES M/F 0805 10E 1%
R384		036-16390-00	RES M/F 0805 390K 5%	R641		036-14150-10	RES M/F 0805 1K5 1%
R385		036-16390-00	RES M/F 0805 390K 5%	R645		036-13470-00	RES M/F 0805 470E 5%
R387		036-15100-10	RES M/F 0805 10K 1%	R649		036-14470-10	RES M/F 0805 4K7 1%
R388		036-15470-10	RES M/F 0805 47K 1%	R653		036-15100-10	RES M/F 0805 10K 1%
R389		036-15470-10	RES M/F 0805 47K 1%	R681		036-13100-10	RES M/F 0805 100E 1%
R391		036-13220-10	RES 0805 220E 1%	R685		036-15150-00	RES M/F 0805 15K 5%
R392		036-14330-10	RES M/F 0805 3K3 1%	R689		036-12100-10	RES M/F 0805 10E 1%
R393		036-16220-00	RES M/F 0805 220K 5%	R693		036-16100-10	RES M/F 0805 100K 1%
R394		036-14100-10	RES M/F 0805 1K 1%	R696		036-15560-10	RES MF 0805 56K 1%
R395		036-14220-00	RES M/F 0805 2K2 5%	R701		036-12220-00	RES M/F 0805 22E 5%
R396		036-15820-00	RES M/F 0805 82K 5%	R702		036-17100-10	RES M/F 0805 1M 1%
R397		036-16560-00	RES M/F 0805 560K 5%	R703		036-17100-10	RES M/F 0805 1M 1%
R400		036-14100-10	RES M/F 0805 1K 1%	R706		036-15150-00	RES M/F 0805 15K 5%
R401		036-14390-10	RES M/F 0805 3K9 1%	R707		036-15470-10	RES M/F 0805 47K 1%
R402		036-14220-00	RES M/F 0805 2K2 5%	R708		036-13100-10	RES M/F 0805 100E 1%
R403		036-12100-10	RES M/F 0805 10E 1%	R709		036-13100-10	RES M/F 0805 100E 1%
R404		036-12330-00	RES M/F 0805 33E 5%	R710		036-13100-10	RES M/F 0805 100E 1%
R407		036-13180-00	RES M/F 0805 180E 5%	R711		036-13100-10	RES M/F 0805 100E 1%
R408		036-17100-10	RES M/F 0805 1M 1%	R712		036-12100-10	RES M/F 0805 10E 1%
R409		036-10000-00	RES M/F 0805 ZERO OHM	R730		036-13470-00	RES M/F 0805 470E 5%
R410		036-12100-10	RES M/F 0805 10E 1%	R731		036-13470-00	RES M/F 0805 470E 5%
R411		036-17100-10	RES M/F 0805 1M 1%	R732		036-13470-00	RES M/F 0805 470E 5%
R414		036-12100-10	RES M/F 0805 10E 1%	R742		036-13150-10	RES M/F 0805 150E 1%
R415		036-14100-10	RES M/F 0805 1K 1%	R743		036-13150-10	RES M/F 0805 150E 1%
R416		036-14390-10	RES M/F 0805 3K9 1%	R744		036-12220-00	RES M/F 0805 22E 5%
R417		036-14220-00	RES M/F 0805 2K2 5%	R746		036-12220-00	RES M/F 0805 22E 5%
R418		036-12100-10	RES M/F 0805 10E 1%	R747		036-12220-00	RES M/F 0805 22E 5%
R421		036-12330-00	RES M/F 0805 33E 5%	R748		036-15470-10	RES M/F 0805 47K 1%
R422		036-13470-00	RES M/F 0805 470E 5%	R749		036-15470-10	RES M/F 0805 47K 1%
R423		036-13470-00	RES M/F 0805 470E 5%	R750		036-12220-00	RES M/F 0805 22E 5%
R424		036-12120-00	RES M/F 0805 12E 5%	R752		036-12220-00	RES M/F 0805 22E 5%
R425		036-13470-00	RES M/F 0805 470E 5%	R753		036-17100-10	RES M/F 0805 1M 1%
R428		036-13470-00	RES M/F 0805 470E 5%	R754		036-14100-10	RES M/F 0805 1K 1%
R429		036-13470-00	RES M/F 0805 470E 5%	R756		036-16470-00	RES M/F 0805 470K 5%
R430		036-12120-00	RES M/F 0805 12E 5%	R757		036-16470-00	RES M/F 0805 470K 5%
R431		036-12470-00	RES M/F 0805 47E 5%	R758		036-14120-00	RES M/F 0805 1K2 5%
R500		036-12100-10	RES M/F 0805 10E 1%	R759		036-13330-00	RES M/F 0805 330E 5%
R501		036-15390-10	RES M/F 0805 39K 1%	R760		036-13180-00	RES M/F 0805 180E 5%
R502		036-13330-00	RES M/F 0805 330E 5%	R762		036-13100-10	RES M/F 0805 100E 1%
R503		036-13220-10	RES 0805 220E 1%	R763		036-13100-10	RES M/F 0805 100E 1%
R505		036-13820-00	RES M/F 0805 820E 5%	R765		036-13680-00	RES M/F 0805 680E 5%
&R506	10	036-12470-00	RES M/F 0805 47E 5%	R766		036-14100-10	RES M/F 0805 1K 1%
&R506	25	036-12470-00	RES M/F 0805 47E 5%	R767		036-13680-00	RES M/F 0805 680E 5%
&R506	30	036-12470-00	RES M/F 0805 47E 5%	R769		036-13180-00	RES M/F 0805 180E 5%
&R507	10	036-12470-00	RES M/F 0805 47E 5%	R771		036-14820-10	RES M/F 0805 8K2 1%
&R507	25	036-12470-00	RES M/F 0805 47E 5%	R772		036-15220-00	RES M/F 0805 22K 5%
&R507	30	036-12470-00	RES M/F 0805 47E 5%	R774		036-14820-10	RES M/F 0805 8K2 1%
R508		036-11470-00	RES M/F 0805 4E7 10%	R775		036-15180-10	RES M/F 0805 18K 1%
R509		036-12100-10	RES M/F 0805 10E 1%	R784		036-12680-00	RES M/F 0805 68E 5%
R511		036-14180-00	RES M/F 0805 1K8 5%	R785		036-14330-10	RES M/F 0805 3K3 1%
&R516	10	036-11330-00	RES M/F 0805 3E3 5%	R786		036-12100-10	RES M/F 0805 10E 1%
&R516	25	036-11470-00	RES M/F 0805 4E7 10%	R787		036-12100-10	RES M/F 0805 10E 1%
&R516	30	036-11470-00	RES M/F 0805 4E7 10%	R790		036-13390-10	RES M/F 0805 390E 1%
R517		036-13100-10	RES M/F 0805 100E 1%	R791		036-14100-10	RES M/F 0805 1K 1%
R518		036-12330-00	RES M/F 0805 33E 5%	R793		036-12180-00	RES M/F 0805 18E 5%
R520		036-14220-00	RES M/F 0805 2K2 5%	R794		036-13120-00	RES M/F 0805 120E 5%
R540		036-12330-00	RES M/F 0805 33E 5%	R804		036-15470-10	RES M/F 0805 47K 1%
R541		036-11470-00	RES M/F 0805 4E7 10%	R805		036-13470-00	RES M/F 0805 470E 5%
R542		036-11470-00	RES M/F 0805 4E7 10%	R808		036-12100-10	RES M/F 0805 10E 1%
R543		036-14180-00	RES M/F 0805 1K8 5%	R809		036-14470-10	RES M/F 0805 4K7 1%
R544		036-14220-00	RES M/F 0805 2K2 5%	R810		036-14470-10	RES M/F 0805 4K7 1%
R545		036-14100-10	RES M/F 0805 1K 1%	R811		036-14470-10	RES M/F 0805 4K7 1%
R546		036-12270-00	RES M/F 0805 27E 5%	R812		036-14470-10	RES M/F 0805 4K7 1%
R547		036-12680-00	RES M/F 0805 68E 5%	R813		036-14470-10	RES M/F 0805 4K7 1%
R548		036-10000-00	RES M/F 0805 ZERO OHM	R815		036-15470-10	RES M/F 0805 47K 1%
R549		036-12120-00	RES M/F 0805 12E 5%	R816		036-16150-00	RES M/F 0805 150K 5%
R550		036-12560-00	RES M/F 0805 56E 5%	R818		036-14470-10	RES M/F 0805 4K7 1%
R554		036-12680-00	RES M/F 0805 68E 5%	R819		036-14470-10	RES M/F 0805 4K7 1%
R557		036-13120-00	RES M/F 0805 120E 5%	R820		036-15470-10	RES M/F 0805 47K 1%
R558		036-12100-10	RES M/F 0805 10E 1%	R821		036-15470-10	RES M/F 0805 47K 1%
R560		036-11470-00	RES M/F 0805 4E7 10%	R822		036-15470-10	RES M/F 0805 47K 1%
R561		036-14330-10	RES M/F 0805 3K3 1%	R823		036-15470-10	RES M/F 0805 47K 1%
R562		036-15150-00	RES M/F 0805 15K 5%	R824		036-14220-00	RES M/F 0805 2K2 5%

Ref	Var	IPN	Description	Ref	Var	IPN	Description
R825		036-14220-00	RES M/F 0805 2K2 5%	&XF302	30	276-00010-68	FLTR XTL 45MHZ 15KHZ 2 POLE
R826		036-14220-00	RES M/F 0805 2K2 5%				
R827		036-14220-00	RES M/F 0805 2K2 5%				
R828		036-14220-00	RES M/F 0805 2K2 5%				
R829		036-14220-00	RES M/F 0805 2K2 5%				
R830		036-14220-00	RES M/F 0805 2K2 5%				
R831		036-14220-00	RES M/F 0805 2K2 5%				
R832		036-14220-00	RES M/F 0805 2K2 5%				
R833		036-14220-00	RES M/F 0805 2K2 5%				
R835		036-14220-00	RES M/F 0805 2K2 5%				
R836		036-14220-00	RES M/F 0805 2K2 5%				
R837		036-14220-00	RES M/F 0805 2K2 5%				
R838		036-14470-10	RES M/F 0805 4K7 1%				
R839		036-14470-10	RES M/F 0805 4K7 1%				
R840		036-14220-00	RES M/F 0805 2K2 5%				
R841		036-14220-00	RES M/F 0805 2K2 5%				
R842		036-14220-00	RES M/F 0805 2K2 5%				
R843		036-14220-00	RES M/F 0805 2K2 5%				
R844		036-15470-10	RES M/F 0805 47K 1%				
R845		036-16150-00	RES M/F 0805 150K 5%				
R846		036-14470-10	RES M/F 0805 4K7 1%				
R847		036-14470-10	RES M/F 0805 4K7 1%				
R848		036-13470-00	RES M/F 0805 470E 5%				
R852		036-14470-10	RES M/F 0805 4K7 1%				
R853		036-13470-00	RES M/F 0805 470E 5%				
R854		036-16330-00	RES M/F 0805 330K 5%				
R855		036-15470-10	RES M/F 0805 47K 1%				
R856		036-16150-00	RES M/F 0805 150K 5%				
R857		036-16150-00	RES M/F 0805 150K 5%				
R858		036-15270-10	RES M/F 0805 27K 1%				
R859		036-17120-10	RES M/F 0805 1M2 1%				
R860		036-16820-10	RES M/F 0805 820K 1%				
R861		036-14510-10	RES M/F 0805 5K1 1%				
R863		036-14470-10	RES M/F 0805 4K7 1%				
R865		036-14270-10	RES M/F 0805 2K7 1%				
R866		036-16820-10	RES M/F 0805 820K 1%				
R867		036-16820-10	RES M/F 0805 820K 1%				
R868		036-14470-10	RES M/F 0805 4K7 1%				
R869		036-15270-10	RES M/F 0805 27K 1%				
R870		036-17120-10	RES M/F 0805 1M2 1%				
R871		036-16820-10	RES M/F 0805 820K 1%				
R872		036-14510-10	RES M/F 0805 5K1 1%				
R873		036-14220-00	RES M/F 0805 2K2 5%				
R875		036-14470-10	RES M/F 0805 4K7 1%				
R876		036-16100-10	RES M/F 0805 100K 1%				
R877		036-16100-10	RES M/F 0805 100K 1%				
R878		036-16100-10	RES M/F 0805 100K 1%				
R879		036-16100-10	RES M/F 0805 100K 1%				
R881		036-15470-10	RES M/F 0805 47K 1%				
R882		036-15470-10	RES M/F 0805 47K 1%				
R884		036-16150-00	RES M/F 0805 150K 5%				
R885		036-16150-00	RES M/F 0805 150K 5%				
R886		036-15100-10	RES M/F 0805 10K 1%				
R887		036-14100-10	RES M/F 0805 1K 1%				
R888		036-14820-10	RES M/F 0805 8K2 1%				
R889		036-16100-10	RES M/F 0805 100K 1%				
R890		036-16150-00	RES M/F 0805 150K 5%				
R891		036-16100-10	RES M/F 0805 100K 1%				
R892		036-16330-00	RES M/F 0805 330K 5%				
R894		036-14470-10	RES M/F 0805 4K7 1%				
R895		036-15100-10	RES M/F 0805 10K 1%				
R897		036-15100-10	RES M/F 0805 10K 1%				
R898		036-16470-00	RES M/F 0805 470K 5%				
R900		036-15100-10	RES M/F 0805 10K 1%				
RL210		237-10010-00	RELAY 12V DPDT 10PIN SMD				
RV205		040-05100-22	POT 10K LOG DUAL PCB 6 OD SFT				
RV210		040-05100-23	POT 10K LOG PCB 15MM SLOT SFT				
RV220		042-05100-05	RES PRESET SMD 10K CER 4MM SQ				
RV230		040-05100-21	POT 10K LIN PCB 15MM SLOT SFT				
RV235		042-05100-05	RES PRESET SMD 10K CER 4MM SQ				
RV345		042-04220-05	RES PRESET SMD 2K CER 4MM SQ				
RV346		042-05100-05	RES PRESET SMD 10K CER 4MM SQ				
SHLD610		062-00010-13	CAN 10MMSQ*11MM CAN SANWA 613				
SK805		240-10000-07	CONN SMD SKT 16W 2R M-MATCH				
SK810		240-04020-42	SKT 44 PIN SMD PLCC				
SW201		230-00010-30	SWITCH TOG SPDT R-ANG PCB MTG				
T210		053-00010-17	XFMR T4030 LINE MATCH POTCORE				
T540		000-10080-00	XSTR SMD BLT80 UHF PWR SOT223				
T610		050-15119-52	COIL SMD 680uH XFMR 5119-T052				
TL500		051-10950-00	COAX RES 950 MHZ 6X6 SMD				
X300		274-00010-22	XTAL 44.545MHZ TE/22 HC45/U				
&XF300A	10	276-00010-86	FLTR XTL 45MHz 15KHz BW 4P				
&XF300A	25	276-00010-87	FLTR XTL 45MHz 7.5KHz BW 4P				
&XF300A	30	276-00010-86	FLTR XTL 45MHz 15KHz BW 4P				
&XF300B	10	276-00010-86	FLTR XTL 45MHz 15KHz BW 4P				
&XF300B	25	276-00010-87	FLTR XTL 45MHz 7.5KHz BW 4P				
&XF300B	30	276-00010-86	FLTR XTL 45MHz 15KHz BW 4P				
&XF302	10	276-00010-68	FLTR XTL 45MHZ 15KHZ 2 POLE				
&XF302	25	276-00010-69	FLTR XTL 45MHZ 7.5KHZ 2 POLE				

T885 Mechanical & Miscellaneous Parts (220-01595-02)

IPN	Legend	Description	IPN	Legend	Description
002-08951-20		S) IC AT89C51 PLCC44 MIC 12MHZ			
066-00010-20		SLUG BRASS A4M764 HELIC RESNTR			
220-01595-02		PCB T885 RX SERIES II			
230-00010-31		SWITCH COVER FOR 230-00010-30			
240-02100-06		SKT COAX N TYPE PNL MTG OP-TER			
303-11169-04		CHASSIS PAINTED T800 SER II			
303-23118-00		COVER A3M2247 D RANGE T855/7			
303-50074-00		CLIP A3M2246 SPRING CLAMP T857			
308-01007-01		HANDLE BS SII 2 WASHERS INC			
308-01048-00		HOUSING A3M2378 DOUBLET H/RES			
311-01015-00		KNOB 15MM & SKIRT 6MM SFT			
312-01052-02		LID TOP T800 SER II PTND			
312-01053-02		LID BOTTOM T800 SER II PNTD			
316-06622-00		PNL FRT RX T800 SERIES II			
349-00020-36		SCREW TT M3X8m PANTORX BLK			
349-00020-43		SCRW T/T M4X12MM P/POZ BZ			
349-00020-45		SCRW T/T M4X20MM P/POZ BZ			
352-00010-29		NUT M4 NYLOC HEX			
352-00010-54		NUT Brass hex 1/4" UNF 3mm			
353-00010-24		WSHR M4x8mm Flat			
356-00010-03		TAG SOLDER 3MM LONG M614/3.2			
362-00010-33		GROMMET LED MTG 3MM			
365-00011-53		LABEL 104*37MM			
365-00100-20		LABEL WHITE S/A 28X11MM			
399-00010-51		BAG PLASTIC 75*100MM			

T885 Grid Reference Index (IPN 220-01595-02)

How To Use This Grid Reference Index

The first digit in the PCB layout reference is a "1" or "2", indicating the top or bottom side layout respectively, and the last two characters give the location of the component on that diagram.

The first digit in the circuit diagram reference is the sheet number, and the last two characters give the location of the component on that sheet.

Device	PCB	Circuit	Device	PCB	Circuit	Device	PCB	Circuit	Device	PCB	Circuit
C201	1:B5	2-B9	&C315	1:E7	3-G7	C409	1:K7	4-G3	C576	1:G5	5-N4
C203	1:C5	2-B8	C316	1:F7	3-G8	C410	1:K8	4-G4	C577	1:G6	5-N2
C205	1:D5	2-B8	C317	1:F7	3-H8	C411	1:J8	4-H5	C578	1:H6	5-N2
C207	1:C5	2-C8	&C318	1:E7	3-H7	C414	1:J8	4-H4	C579	1:H6	5-N2
C209	1:C6	2-E8	C321	1:E7	3-H7	C415	1:J8	4-H4	C585	1:G6	5-N2
C210	1:C5	2-D7	C322	1:E7	3-H7	C417	1:H8	4-L3	C586	1:G5	5-N4
C211	1:C4	2-D7	C324	1:E7	3-J7	C418	1:H8	4-M3	C587	1:G6	5-Q2
C212	1:C5	2-E8	C325	1:F7	3-J8	C422	1:G8	4-M4	C588	1:G6	5-Q2
C213	1:C5	2-E7	C328	1:E6	3-J8	C500	1:J4	5-D8	C590	1:J6	5-A8
C215	1:C4	2-E7	&C329	1:E7	3-K8	C501	1:J4	5-E8	C591	1:K6	5-B8
C217	1:C4	2-E7	&C330	1:E6	3-K8	C502	1:J5	5-E8	C592	1:K6	5-B8
C219	1:C5	2-H6	&C331	1:F6	3-L8	C503	1:J4	5-E8	C593	1:J6	5-B8
C221	1:C5	2-H6	&C332	1:E6	3-L8	C504	1:J5	5-F7	C594	1:J6	5-C8
C222	1:B5	2-J9	&C335	1:E6	3-M8	C505	1:K5	5-G7	C595	1:J6	5-C8
C223	1:B5	2-H8	C336	1:E6	3-M8	C506	1:J5	5-G6	C596	1:J5	5-C8
C225	1:B5	2-J8	C337	1:E6	3-M7	C507	1:J4	5-G7	C597	1:J5	5-D8
C227	1:B5	2-J8	C338	1:E5	3-M8	C508	1:J5	5-G7	C610A	1:M5	6-B6
C229	1:B6	2-K8	C339	1:E6	3-N8	C509	1:J5	5-G6	C610B	1:M5	6-B6
C231	1:B6	2-K8	C340	1:E3	3-N0	C510	1:J5	5-G7	C611A	1:M5	6-D6
C233	1:B5	2-J7	C341	1:E3	3-N0	C516	1:J5	5-G6	C611B	1:M4	6-D6
C235	1:B6	2-M6	C342	1:E5	3-B3	&C517	1:J5	5-H6	C623	1:N6	6-N8
C237	1:B6	2-M5	C343	1:E5	3-C3	C518	1:K5	5-J7	C625	1:M6	6-Q8
C238	1:B6	2-N7	C345	1:F4	3-D4	&C519	1:J5	5-J6	C626	1:M6	6-R8
C239	1:C6	2-P6	C346	1:F3	3-G0	C520	1:K5	5-J7	C628	1:M6	6-R8
C240A	1:D5	2-Q8	C347	1:E4	3-D4	&C521	1:J5	5-J5	C630	1:N5	6-K4
C240B	1:D5	2-R8	C348	1:E5	3-E4	&C522	1:J5	5-J6	C631A	1:M5	6-M6
C240C	1:D6	2-R8	C349	1:E5	3-E3	&C524	1:K5	5-K6	C631B	1:N4	6-M6
C249	1:D6	2-Q7	C350	1:E5	3-E4	&C525	1:K5	5-K6	C637	1:M6	6-P5
C251	1:C6	2-R7	C351	1:F3	3-E0	C531	1:J5	5-K6	C640	1:M5	6-G0
C253	1:D4	2-G5	C352	1:E3	3-F2	&C533	1:K5	5-L6	C650	1:N5	6-L4
C255	1:C7	2-L2	C353	1:F5	3-F3	C536	1:K4	5-Q6	C651	1:M5	6-M4
C257	1:C7	2-M2	C354	1:F4	3-G3	C537	1:K5	5-Q6	C658	1:L5	6-K1
C259	1:C7	2-M3	C355	1:F4	3-H2	C540	1:H6	5-D2	C660	1:L5	6-K1
C260A	1:D7	2-N4	C356	1:F4	3-H3	C541	1:H6	5-D1	C665	1:L5	6-L1
C260B	1:D7	2-M4	C357	1:F4	3-G4	C542	1:H6	5-E3	C670	1:L5	6-L1
C260C	1:D8	2-M4	C358	1:F4	3-L5	C543	1:J6	5-E2	C673	1:L5	6-N2
C261	1:C7	2-N2	C359	1:E3	3-H4	C544	1:H5	5-E1	C677	1:L6	6-P1
C262	1:D7	2-P3	C360	1:F3	3-J3	C545	1:J6	5-E2	C681	1:L6	6-Q2
C264	1:C7	2-P2	C361	1:E4	3-K3	C546	1:J5	5-F1	C684	1:M6	6-Q2
C266	1:D2	2-R3	C362	1:E4	3-K3	C547	1:J5	5-F0	C687	1:L6	6-P1
C268	1:D3	2-R3	C364	1:E4	3-M3	C548	1:J5	5-F0	C690	1:L6	6-Q1
C270	1:C8	2-E3	C365	1:E4	3-N3	C549	1:J6	5-F2	C693	1:L6	6-Q1
C272	1:C8	2-D2	C366	1:D5	3-M2	C555	1:J5	5-F0	C700	1:J4	7-A8
C273	1:C9	2-C1	C367	1:E3	3-K4	C556	1:H5	5-G3	C702	1:J4	7-B8
C274	1:C8	2-E2	C368	1:E4	3-L4	C557	1:J5	5-G0	C703	1:J3	7-B8
C276	1:D8	2-B0	C369	1:E4	3-L3	C558	1:J5	5-G0	C705	1:J3	7-C7
C278	1:D8	2-C0	C371	1:F3	3-E1	C559	1:H5	5-H4	C707	1:J2	7-B5
C280	1:D9	2-F1	C385	1:F8	3-P8	C560	1:G5	5-J4	C708	1:J3	7-C5
C286	1:B8	2-F1	C386	1:F8	3-P8	C561	1:H6	5-J2	C709	1:H3	7-C5
C300	1:F8	3-C7	C387	1:F7	3-R8	C562	1:G5	5-K4	C710A	1:H3	7-P7
C302	1:F8	3-D6	C389	1:F7	3-R8	C563	1:G5	5-L2	C710B	1:J4	7-Q7
C303	1:F8	3-E7	C390	1:E4	3-M0	C564	1:G5	5-K4	C710C	1:J3	7-P7
C304	1:E8	3-E8	C400	1:N8	4-C3	C569	1:G5	5-L4	C711	1:J2	7-E7
C307	1:E8	3-E8	C401	1:N8	4-D4	C570	1:H5	5-L2	C712	1:H2	7-E7
C308	1:E8	3-E8	C402	1:N8	4-D5	C571	1:G5	5-J2	C713	1:H2	7-E7
&C309	1:F8	3-E7	C403	1:M8	4-E4	C572	1:H6	5-L2	C735	1:J2	7-A1
C310	1:E8	3-E8	C404	1:N8	4-E3	C573	1:H5	5-M4	C736	1:H2	7-B1
&C311	1:F8	3-F7	C407	1:N7	4-E5	C574	1:G6	5-M4	C740A	1:H2	7-B4
&C314	1:E8	3-G7	C408	1:K7	4-G5	C575	1:H6	5-N2	C740B	1:G2	7-B3

Device	PCB	Circuit	Device	PCB	Circuit	Device	PCB	Circuit	Device	PCB	Circuit
C741A	1:H2	7-C4	D289	1:B2	2-K0	IC830	1:N4	8-K0	P254	1:B2	2-K9
C741B	1:G2	7-C3	D290	1:B2	2-L0	IC830	1:N4	8-D0	P256	1:B2	2-L8
C742A	1:H2	7-D4	D295	1:B2	2-L0	IC830	1:N4	8-F2	P258	1:D3	2-P8
C742B	1:H2	7-D3	D330	1:E4	3-L4	IC830	1:N4	8-D2	P260	1:D3	2-P7
C743	1:H2	7-B1	D330	1:E4	3-L3	IC840	1:M2	8-L0	P263	1:C2	2-R6
C745	1:G3	7-D1	D500	1:K5	5-N7	IC850	1:M3	8-P1	P266	1:C2	2-R5
C750	1:H4	7-R7	D501	1:K5	5-N6	IC850	1:M3	8-Q2	P268	1:C2	2-R5
C757	1:G4	7-G5	D502	1:K5	5-N6	IC850	1:M3	8-M2	P270	1:C1	2-R5
C759	1:G4	7-G4	D503	1:K5	5-N6	IC850	1:M3	8-M2	P280	1:C2	2-R4
C761	1:G3	7-J4	D504	1:K5	5-P6	IC850	1:M3	8-M0	P282	1:C2	2-R4
C762	1:G3	7-K4	D505	1:K5	5-P6				P284	1:B4	2-R4
C764	1:G3	7-J2	D610	1:N6	6-L6	L230	1:D2	2-K2	P287	1:B2	2-R0
C765	1:G3	7-J2	D610	1:N6	6-M6	L300	1:F8	3-D7	P810	1:K2	8-A5
C767	1:H3	7-K3	D640	1:L5	6-M1	L301	1:E8	3-E8	P815	1:L4	8-C4
C769	1:H3	7-M4	D640	1:L5	6-M2	L302	1:F8	3-E7	P820	1:K4	8-L8
C770	1:H3	7-M4	D645	1:M5	6-H0	&L303	1:E7	3-H7	P825	1:K4	8-L8
C772	1:G3	7-M2	D730A	1:H3	7-H1	&L304	1:E6	3-K8	P830	1:K4	8-L8
C774	1:H4	7-N2	D740A	1:H3	7-K2	&L307	1:E6	3-L8	P835	1:K4	8-L7
C776	1:H4	7-M1	D820A	1:J3	8-B7	L308	1:E6	3-M8	P840	1:K4	8-L7
C780	1:G3	7-N1	D860	1:M2	8-P0	L345	1:F5	3-E4			
C782	1:G2	7-N0	D860	1:M2	8-P0	L400	1:N8	4-D4	PIN4	1:J4	7-B8
C784	1:G3	7-Q1	D880	1:M2	8-R2	L401	1:N7	4-D3			
C786	1:G3	7-Q1	D880	1:M2	8-R2	L402	2:M7	4-F3	PL100	1:P3	1-A0
C788	1:G3	7-P0				L403	2:M8	4-F3	PL200	1:C6	2-R7
C790	1:G4	7-Q0	#H400	1:M8	4-F4	L404	1:K8	4-H4	PL210	1:C5	2-B8
C792	1:G4	7-Q0	#H401	1:J8	4-K4	L407	1:K7	4-H3	PL220	1:B5	2-H7
C810	1:L4	8-J8	#H900	1:P8	9-D5	L408	2:J7	4-K3	PL230	1:B2	2-L8
C812	1:K2	8-F4				L409	2:J8	4-K3	PL240	1:B6	2-K7
C813	1:J3	8-J5	IC210	1:C5	2-F7	L410	1:H8	4-L3	PL250	1:C8	2-C3
C814	1:L2	8-F6	IC210	1:C5	2-G7	L414	1:G8	4-L4	PL260	1:C4	2-H3
C815	1:N3	8-B1	IC210	1:C5	2-C7	L500	1:K5	5-J7	PL270	1:C2	2-L1
C816	1:N3	8-B1	IC240	1:C6	2-P7	L501	1:K5	5-J7			
C818	1:N3	8-C1	IC260	1:C7	2-N2	L502	1:K5	5-M6	Q210	1:B5	2-J8
C819	1:N3	8-C1	IC270	1:C8	2-B2	L503	1:K5	5-M6	Q220	1:B6	2-M6
C820	1:N4	8-D1	IC270	1:C8	2-F3	L504	1:K5	5-P6	Q230	1:B6	2-N6
C822	1:N3	8-D2	IC270	1:C8	2-E2	L505	1:K5	5-P6	Q240	1:C4	2-H4
C824	1:N3	8-D2	IC280	1:D8	2-E1	L540	1:H6	5-K2	Q245	1:B6	2-J4
C826	1:N3	8-D0	IC280	1:D8	2-B0	L541	1:H6	5-N2	Q250	1:C8	2-G2
C828	1:N3	8-D0	IC280	1:D8	2-D0	L543	1:G6	5-P2	Q255	1:C7	2-H2
C830	1:M4	8-K0	IC300	1:E5	3-K0	L700	1:G4	7-Q0	Q260	1:B7	2-K0
C832	1:M3	8-E2	IC300	1:E5	3-M8	L900	1:P6	9-F5	Q270	1:B8	2-K0
C833	1:M4	8-E2	IC300	1:E5	3-K0	L901	1:P6	9-F5	Q280	1:B7	2-L2
C834	1:M3	8-F1	IC300	1:E5	3-D3	L902	1:P6	9-G5	Q290	1:B7	2-M2
C836	1:M3	8-E0	IC330	1:E4	3-J3	L904	2:P8	9-D4	Q300	1:F8	3-D7
C837	1:M3	8-E0	IC330	1:E4	3-P1	L905	2:P7	9-E4	Q301	1:F7	3-J8
C838	1:N4	8-F0	IC330	1:E4	3-K3				Q302	1:E7	3-J7
C840	1:M2	8-K2	IC330	1:E4	3-M0	LINK1	1:B3	2-Q3	Q346	1:F3	3-G0
C842	1:N2	8-L0	IC330	1:E4	3-G3	LINK2	1:A4	2-Q2	Q400	1:N8	4-C4
C844	1:N3	8-L0	IC345	1:E5	3-D3				Q401	1:N7	4-D3
C846	1:N2	8-M0	IC351	1:E3	3-N0	M400	1:G8	4-L3	Q402	1:K8	4-G4
C848	1:N2	8-M0	IC351	1:E3	3-E1				Q403	1:K7	4-H3
C850	1:M2	8-N0	IC351	1:E3	3-G0	P100	1:P6	1-R8	Q500	1:J5	5-D6
C873	1:M3	8-N2	IC352	1:E3	3-H1	P160	1:P2	1-Q4	Q501	1:J5	5-E7
C876	1:M4	8-P2	IC352	1:E3	3-F1	P170	1:P2	1-R4	Q502	1:J5	5-F7
C879	1:M4	8-Q1	IC352	1:E3	3-M0	P201	1:C8	2-A9	Q503	1:K5	5-G7
C900	1:P7	9-E4	IC360	1:F8	3-Q8	P204	1:D4	2-A9	Q504	1:K5	5-J6
C901	1:P6	9-F4	IC610	1:M5	6-C6	P207	1:C5	2-A8	Q540	1:J6	5-E1
C902	1:P6	9-G4	IC630	1:N5	6-K5	P210	1:D5	2-C7	Q541	1:J5	5-E0
C903	1:P6	9-H4	IC640	1:M5	6-N5	P213	1:D3	2-A7	Q542	1:G5	5-J3
			IC640	1:M5	6-J0	P216	1:D4	2-A7	Q543	1:H6	5-J1
CV500	1:K5	5-L6	IC640	1:M5	6-G0	P219	1:D3	2-A7	Q544	1:G5	5-K3
			IC650	1:L5	6-C2	P222	1:B9	2-A6	Q545	1:G6	5-M3
%D111	1:P4	1-R1	=IC700	1:J3	7-A8	P225	1:C4	2-A4	Q546	1:G6	5-P3
%D111A	1:P5	1-Q1	IC710	1:H3	7-P7	P228	1:C4	2-A4	Q590	1:J6	5-C8
D220	1:C4	2-E4	IC710	1:H3	7-J0	P231	1:C9	2-A4	Q591	1:J6	5-C8
D220	1:C4	2-E4	IC710	1:H3	7-D7	P234	1:C4	2-A3	Q592	1:J6	5-C8
D230	1:C6	2-J5	IC710	1:H3	7-C6	P236	1:C8	2-A1	Q620	1:N6	6-P8
D230	1:C6	2-J5	IC710	1:H3	7-D6	P238	1:D8	2-A1	Q630	1:M6	6-P5
D240	1:C8	2-D2	IC710	1:H3	7-D6	P240	1:C7	2-G2	Q660	1:L5	6-N1
D240	1:C8	2-D3	IC710	1:H3	7-C6	P242	1:C4	2-G1	Q670	1:L6	6-P2
D250	1:B7	2-H1	IC740	1:H2	7-D1	P244	1:C4	2-G8	Q750	1:G4	7-G3
D260	1:B7	2-H1	IC750	1:H4	7-M3	P246	1:B5	2-H9	Q760	1:G3	7-J3
D270	1:B7	2-J1	IC750	1:H4	7-Q7	P248	1:A5	2-H9	Q770	1:H3	7-J1
D270	1:B7	2-J1	IC750	1:H4	7-H5	P249	1:A5	2-K9	Q775	1:H3	7-K3
D280	1:B7	2-K1	IC820	1:L4	8-N4	P250	1:B2	2-K9	Q780	1:H3	7-K3
D285	1:D2	2-L1	IC830	1:N4	8-F0	P252	1:B2	2-K9	Q785	1:H3	7-K2

Device	PCB	Circuit	Device	PCB	Circuit	Device	PCB	Circuit	Device	PCB	Circuit
Q790	1:H3	7-L3	R288	1:B8	2-F1	R403	1:N7	4-D5	R629	1:M6	6-P6
Q795	1:G3	7-P0	R289	1:C4	2-G3	R404	1:N8	4-D4	R633	1:M5	6-Q8
Q810	1:K2	8-B6	R290	1:C4	2-H4	R407	1:M8	4-D4	R636	1:M5	6-K6
Q820	1:K2	8-B6	R292	1:C7	2-G2	R408	1:M8	4-E3	R637	1:N5	6-K5
Q840	1:K2	8-F5	R293	1:B7	2-H1	R409	1:N7	4-E3	R640	1:M5	6-G0
Q850	1:L2	8-G5	R294	1:B8	2-H0	R410	1:N7	4-E5	R641	1:N5	6-L4
Q860	1:K4	8-B4	R295	1:B6	2-J1	R411	1:M7	4-E3	R645	1:N5	6-L5
Q870	1:L4	8-C3	R296	1:B7	2-K1	R414	1:K7	4-F5	R649	1:M5	6-M5
Q880	1:L2	8-Q3	R297	1:B2	2-M0	R415	1:K8	4-G5	R653	1:M5	6-Q4
Q890	1:L4	8-H3	R298	1:B7	2-J0	R416	1:K8	4-G4	R681	1:L5	6-L2
Q895	1:M3	8-P2	R299	1:B7	2-J0	R417	1:K8	4-G4	R685	1:L5	6-N2
			R300	1:F8	3-D6	R418	1:K7	4-H5	R689	1:L6	6-Q3
R160	1:P2	1-Q4	R301	1:E9	3-E9	R421	1:J8	4-H5	R693	1:L5	6-P1
R201	1:C5	2-B8	R302	1:E8	3-E8	R422	1:J8	4-H4	R696	1:L6	6-P1
R202	1:C5	2-B7	R303	1:E8	3-E8	R423	1:J8	4-J3	R701	1:J4	7-A9
R204	1:C5	2-C9	R304	1:F7	3-G8	R424	1:J7	4-J4	R702	1:J4	7-B9
R205	1:C5	2-C8	R307	1:F7	3-H8	R425	1:J7	4-J3	R703	1:H4	7-B8
R207	1:C5	2-D8	R308	1:E7	3-H8	R428	1:G8	4-K5	R706	1:J3	7-C6
&R209	1:C4	2-D8	R309	1:E7	3-H7	R429	1:G8	4-K4	R707	1:J3	7-C7
R210	1:C5	2-D8	R310	1:E7	3-J7	R430	1:G8	4-L4	R708	1:J2	7-D7
R211	1:C5	2-E8	R311	1:F7	3-J9	R431	1:G8	4-L3	R709	1:J2	7-E7
R213	1:C5	2-G6	&R312	1:E7	3-J8	R500	1:J5	5-D8	R710	1:J3	7-B6
R215	1:B5	2-G9	R314	1:F7	3-J8	R501	1:J5	5-D7	R711	1:J3	7-C6
R218	1:C5	2-G8	R315	1:E6	3-L8	R502	1:J5	5-E6	R712	1:J3	7-P8
&R219	1:C5	2-G7	R316	1:E6	3-N7	R503	1:J5	5-F8	R730	1:J2	7-A2
R221	1:C5	2-H7	R344	1:E5	3-C3	R505	1:J5	5-G7	R731	1:J2	7-A2
R222	1:C5	2-H7	R345	1:E5	3-C3	&R506	1:J4	5-G8	R732	1:J2	7-A2
%R223	1:A5	2-J9	R347	1:F5	3-D4	&R507	1:J4	5-G8	R742	1:G2	7-C4
R224	1:B5	2-J8	&R349	1:E5	3-F4	R508	1:K5	5-H7	R743	1:H2	7-C4
R225	1:B5	2-J8	R350	1:E5	3-D3	R509	1:J5	5-H6	R744	1:G2	7-D4
R227	1:B5	2-J7	R351	1:F3	3-G0	R511	1:J5	5-F6	R746	1:H2	7-D4
R229	1:B6	2-L6	R352	1:F3	3-G1	&R516	1:J5	5-J6	R747	1:H3	7-D4
R230	1:C6	2-M5	R353	1:D3	3-G1	R517	1:J5	5-K6	R748	1:J2	7-A1
R232	1:B5	2-M7	R354	1:E3	3-H1	R518	1:J5	5-K5	R749	1:H2	7-B1
R233	1:B6	2-M7	R355	1:E5	3-E4	R520	1:K4	5-Q6	R750	1:H4	7-Q8
R234	1:B6	2-N7	R356	1:E3	3-F2	R540	1:J5	5-E0	R752	1:G4	7-F5
R236	1:B5	2-N7	R357	1:E3	3-E2	R541	1:J6	5-E3	R753	1:G4	7-F3
R238	1:C6	2-R6	R358	1:E3	3-H0	R542	1:H6	5-E3	R754	1:G3	7-F3
R239	1:C6	2-R7	R359	1:E3	3-F2	R543	1:J6	5-E2	R756	1:G3	7-G5
R241	1:D4	2-G5	R362	1:D3	3-F1	R544	1:J5	5-E1	R757	1:G4	7-H4
R242	1:C4	2-G4	R363	1:F5	3-G3	R545	1:J5	5-E0	R758	1:H3	7-J4
R244	1:C4	2-G4	R364	1:F4	3-G3	R546	1:H6	5-E1	R759	1:H3	7-J4
R245	1:C4	2-H5	R365	1:D3	3-G2	R547	1:J6	5-E2	R760	1:H3	7-K4
R247	1:C7	2-J5	R366	1:F3	3-D1	R548	1:J6	5-E2	R762	1:H3	7-K4
R249	1:C6	2-J4	R367	1:F3	3-D1	R549	1:J5	5-E1	R763	1:H3	7-L4
R251	1:B7	2-L3	R368	1:F4	3-H3	R550	1:J5	5-E0	R765	1:H3	7-J2
R252	1:C6	2-L3	R369	1:F3	3-E0	R554	1:H5	5-F3	R766	1:G3	7-J3
R254	1:B7	2-L3	R370	1:F3	3-E0	R556	1:J6	5-F2	R767	1:H3	7-K2
R255	1:B7	2-L3	R371	1:F3	3-E0	R557	1:H5	5-G2	R769	1:H3	7-K3
R256	1:C6	2-M3	R372	1:F4	3-H3	R558	1:H6	5-G2	R771	1:H4	7-L3
R258	1:C7	2-M3	R373	1:E3	3-E1	R559	1:H6	5-G2	R772	1:G3	7-L2
R260	1:C7	2-P2	R374	1:F4	3-K5	R560	1:G5	5-H4	R774	1:H3	7-L2
R261	1:C7	2-P3	R375	1:F4	3-K5	R561	1:G5	5-J4	R775	1:H3	7-M2
R262	1:B4	2-P3	R376	1:E3	3-J1	R562	1:G5	5-J2	R784	1:G3	7-P1
%R263	1:C4	2-Q3	R377	1:E4	3-G4	R563	1:G5	5-K2	R785	1:G3	7-P1
R264	1:B8	2-B3	R378	1:E3	3-J1	R564	1:G5	5-K4	R786	1:G3	7-Q1
R265	1:B8	2-B2	R379	1:F3	3-J3	R571	1:G5	5-L4	R787	1:G3	7-Q1
R266	1:B8	2-B2	R380	1:F3	3-J3	R572	1:H6	5-M2	R790	1:G3	7-P0
R267	1:C8	2-C3	R381	1:F3	3-J3	R573	1:H6	5-M2	R791	1:G4	7-P0
%R268	1:C3	2-Q2	R382	1:E3	3-H4	R574	1:H6	5-M2	R793	1:G3	7-P0
R269	1:C8	2-B1	R384	1:E3	3-K4	R575	1:G5	5-M4	R794	1:G3	7-P1
R271	1:D8	2-A0	R385	1:E4	3-K3	R576	1:G5	5-M2	R804	1:J3	8-B7
R272	1:D8	2-B1	R387	1:E4	3-M3	R577	1:G6	5-P2	R805	1:J3	8-B7
R273	1:D8	2-C1	R388	1:E4	3-M4	R578	1:G5	5-P4	R808	1:K2	8-A6
R274	1:B3	2-P3	R389	1:E4	3-M4	R579	1:G6	5-P2	R809	1:K2	8-B6
R275	1:D8	2-C1	%R390	1:D5	3-M2	R580	1:H6	5-N2	R810	1:L2	8-C6
R276	1:B3	2-Q3	R391	1:D5	3-M2	R585	1:G6	5-P4	R811	1:L2	8-C6
R277	1:D8	2-C0	R392	1:F3	3-D2	R586	1:G6	5-P2	R812	1:K2	8-B6
R278	1:D8	2-D1	R393	1:F3	3-D1	R590	1:J6	5-B8	R813	1:K2	8-B5
R279	1:B3	2-Q2	R394	1:F3	3-D1	R591	1:J6	5-C8	R815	1:K2	8-F4
R280	1:C8	2-D3	R395	1:F3	3-D1	R592	1:J6	5-C7	R816	1:K2	8-F4
R281	1:C8	2-D2	R396	1:E3	3-H1	R615	1:M5	6-B6	R818	1:K2	8-G5
R282	1:C8	2-E2	R397	1:E3	3-H1	R617	1:M5	6-D5	R819	1:L2	8-G4
R284	1:C8	2-F3	R400	1:N8	4-C4	R619	1:N6	6-L8	R820	1:K4	8-B4
R285	1:B8	2-F2	R401	1:N8	4-C4	R621	1:N6	6-L8	R821	1:L4	8-B4
R287	1:C8	2-F2	R402	1:N8	4-C4	R625	1:N6	6-L7	R822	1:L4	8-C3

<u>Device</u>	<u>PCB</u>	<u>Circuit</u>	<u>Device</u>	<u>PCB</u>	<u>Circuit</u>	<u>Device</u>	<u>PCB</u>	<u>Circuit</u>	<u>Device</u>	<u>PCB</u>	<u>Circuit</u>
R823	1:L4	8-D3	RV345	1:F3	3-E0						
R824	1:K4	8-L8	RV346	1:F3	3-J3						
R825	1:K4	8-L8									
R826	1:K4	8-L8	SHLD610	1:L6	6-J3						
R827	1:K4	8-L7									
R828	1:K4	8-L7	SK805	1:K3	8-Q9						
R829	1:K4	8-Q9	SK805	1:K3	8-Q6						
R830	1:K3	8-Q9	SK805	1:K3	8-Q9						
R831	1:K3	8-Q9	SK805	1:K3	8-Q7						
R832	1:K3	8-Q8	SK805	1:K3	8-Q6						
R833	1:K3	8-Q8	SK805	1:K3	8-Q9						
R835	1:K3	8-Q8	SK805	1:K3	8-Q7						
R836	1:K3	8-Q8	SK805	1:K3	8-Q8						
R837	1:K3	8-Q7	SK805	1:K3	8-Q6						
R838	1:L4	8-K6	SK805	1:K3	8-Q8						
R839	1:L4	8-L6	SK805	1:K3	8-Q6						
R840	1:K3	8-Q7	SK805	1:K3	8-Q8						
R841	1:K3	8-Q7	SK805	1:K3	8-Q7						
R842	1:K3	8-Q6	SK805	1:K3	8-Q8						
R843	1:K3	8-Q6	SK805	1:K3	8-Q7						
R844	1:L2	8-R3	SK805	1:K3	8-Q5						
R845	1:L2	8-R3	SK810	1:L3	8-H5						
R846	1:L4	8-L6									
R847	1:L4	8-L6	SL210	1:C8	2-E2						
R848	1:L4	8-R5	SL220	1:C8	2-D2						
R852	1:L2	8-G6									
R853	1:L2	8-F6	SW201	1:B4	2-A6						
R854	1:N3	8-C2									
R855	1:N3	8-C1	T210	1:C3	2-Q2						
R856	1:N3	8-C1	T540	1:G6	5-P2						
R857	1:N4	8-D1	T610	1:L6	6-N2						
R858	1:N3	8-C0									
R859	1:N3	8-D0	&TL500	1:K6	5-K6						
R860	1:N3	8-D0									
R861	1:M3	8-D0	TP202	1:C8	2-D9						
R863	1:N3	8-D1	TP211	1:D3	2-P8						
R865	1:M3	8-E2	TP300	1:F8	3-C8						
R866	1:M3	8-F1	TP301	1:E8	3-E7						
R867	1:M3	8-F2	TP345	1:E4	3-M4						
R868	1:N4	8-E0	TP400	1:G8	4-M4						
R869	1:M3	8-E0	TP401	2:G6	4-M5						
R870	1:M3	8-E0	TP601	1:N5	6-K9						
R871	1:N3	8-F0	TP602	1:L5	6-R9						
R872	1:N4	8-F0	TP603	1:L5	6-J2						
R873	1:N4	8-G0	TP604	1:L4	6-N6						
R875	1:M4	8-F2	TP607	1:M4	6-E6						
R876	1:M3	8-K1	TP710	1:G4	7-J5						
R877	1:M2	8-K1									
R878	1:M2	8-K0	X300	1:E6	3-M7						
R879	1:M2	8-K0									
R881	1:L4	8-H3	&XF300A	1:E8	3-F7						
R882	1:M4	8-H3	&XF300B	1:E8	3-G7						
R884	1:M3	8-N3	&XF302	1:E6	3-L8						
R885	1:M3	8-N2									
R886	1:M3	8-P3									
R887	1:M3	8-P3									
R888	1:M3	8-P2									
R889	1:M3	8-N1									
R890	1:M3	8-P1									
R891	1:M2	8-P1									
R892	1:M2	8-P0									
R894	1:M2	8-Q1									
R895	1:M2	8-Q1									
R897	1:M2	8-Q2									
R898	1:M2	8-Q2									
R900	1:P6	9-H4									
RL210	1:C2	2-Q4									
RL210	1:C2	2-K1									
RL210	1:C2	2-Q5									
RV205	1:B5	2-M7									
RV210	1:B7	2-K3									
RV220	1:D4	2-G5									
RV230	1:B8	2-B2									
RV235	1:D9	2-C0									