

7.7 T2000-800 RF PCB

T2000-800 Parts List (IPN 220-01305-03)

Parts List Amendments

R258: Changed from 10Ω to 0Ω (IPN 036-10000-00) to improve power output (6/05/97)
 Mechanical parts corrections: Delete IPN 362-00010-08 (insulating gasket)
 Add IPN 240-02100-11 (BNC socket)
 Add IPN 353-00020-12 (0.9mm flat washer)

Ref	Var	IPN	Description	Ref	Var	IPN	Description
C1		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C213		020-58470-05	CAP ELECT AI RDL 47M 16V 6.3X7MM
C2		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C214		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C3		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C215		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR
C100		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V	C216		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V
C104		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C217		020-58470-05	CAP ELECT AI RDL 47M 16V 6.3X7MM
C106		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C218		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR
C107		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C219		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR
C108		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C220		022-55100-10	CAP MYLAR AI 10N 5% 63V POTTED
C109		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C221		022-57100-02	CAP MYLAR AI 1M 20% 50V POTTED
C110		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C222		022-06100-15	CAP MET POLYSTR 100N 5% 50V 5.6MM HI
C124		015-21330-01	CAP CER 0805 CHIP 3P3 +/-0.25P NPO 50V	C223		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C125		015-21180-01	CAP CER 0805 CHIP 1P8 +/-0.25 NPO 50V	C224		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C126		015-21330-01	CAP CER 0805 CHIP 3P3 +/-0.25P NPO 50V	C225		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C127		015-21680-01	CAP CER 0805 CHIP 6P8 +/-0.25P NPO 50V	C226		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V
C128		015-22220-01	CAP CER 0805 CHIP 22P 5% NPO 50V	C227		015-21560-01	CAP CER 0805 CHIP 5P6 +/-0.25P NPO 50V
C129		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V	C229		020-58470-05	CAP ELECT AI RDL 47M 16V 6.3X7MM
C130		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V	C230		015-22220-01	CAP CER 0805 CHIP 22P 5% NPO 50V
C133		015-22330-01	CAP CER 0805 CHIP 39P 5% NPO 50V	C231		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V
C134		015-21560-01	CAP CER 0805 CHIP 5P6 +/-0.25P NPO 50V	C232		015-21120-01	CAP CER 0805 CHIP 1P2 +/-0.25 NPO 50V
C135		015-22150-01	CAP CER 0805 CHIP 15P 5% NPO 50V	C233		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR
C136		015-21680-01	CAP CER 0805 CHIP 6P8 +/-0.25P NPO 50V	C235		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V
C137		015-23120-01	CAP CER 0805 CHIP 120P 5% NPO 50V	C236		015-21330-01	CAP CER 0805 CHIP 3P3 +/-0.25P NPO 50V
C138		015-21680-01	CAP CER 0805 CHIP 6P8 +/-0.25P NPO 50V	C237		015-21330-01	CAP CER 0805 CHIP 3P3 +/-0.25P NPO 50V
C139		015-22150-01	CAP CER 0805 CHIP 15P 5% NPO 50V	C238		015-21390-01	CAP CER 0805 CHIP 3P9 +/-0.25P NPO 50V
C140		015-21560-01	CAP CER 0805 CHIP 5P6 +/-0.25P NPO 50V	C240		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C141		015-22390-01	CAP CER 0805 CHIP 39P 5% NPO 50V	C241		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C142		015-21560-01	CAP CER 0805 CHIP 5P6 +/-0.25P NPO 50V	C242		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V
C149		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C243		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C158		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	C244		015-22560-01	CAP CER 0805 CHIP 56P 5% NPO 50V
C174		020-58470-05	CAP ELECT AI RDL 47M 16V 6.3X7MM	C245		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V
C175		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C246		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C176		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C247		015-21270-01	CAP CER 0805 CHIP 2P7 +/-0.25P NPO 50V
C179		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V	C248		020-09100-07	CAP ELECT 100M 10V 6.3X7MM 5MM
C180		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C249		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C181		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C250		015-22220-01	CAP CER 0805 CHIP 22P 5% NPO 50V
C182		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C251		015-23120-01	CAP CER 0805 CHIP 120P 5% NPO 50V
C184		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C252		015-22180-01	CAP CER 0805 CHIP 18P 5% NPO 50V
C185		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V	C253		015-22120-01	CAP CER 0805 CHIP 12P 5% NPO 50V
C186		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V	C254		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C187		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	C255		015-21270-01	CAP CER 0805 CHIP 2P7 +/-0.25P NPO 50V
C188		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C256		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C189		015-23470-08	CAP CER 0805 CHIP 470P 10% X7R 50V	C301		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C190		015-23470-08	CAP CER 0805 CHIP 470P 10% X7R 50V	C303		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C191		015-23560-08	CAP CER 0805 CHIP 560P 10% X7R 50V	C304		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C192		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C305		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C193		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR	C306		015-21390-01	CAP CER 0805 CHIP 3P9 +/-0.25P NPO 50V
C194		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C307		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V
C195		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	C308		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C197		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C309		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C198		015-21100-01	CAP CER 0805 CHIP 1P0 +/-0.25P NPO 50V	C310		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V
C199		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	C311		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C200		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V	C312		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C201		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C313		015-21470-01	CAP CER 0805 CHIP 4P7 +/-0.25P NPO 50V
C202		015-22220-01	CAP CER 0805 CHIP 22P 5% NPO 50V	C314		015-21470-01	CAP CER 0805 CHIP 4P7 +/-0.25P NPO 50V
C203		015-25220-08	CAP CER 0805 CHIP 22N 10% X7R 50V	C315		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C204		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C316		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V
C205		015-25220-08	CAP CER 0805 CHIP 22N 10% X7R 50V	C317		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C206		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C318		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C207		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V	C319		015-21330-01	CAP CER 0805 CHIP 3P3 +/-0.25P NPO 50V
C208		015-23100-01	CAP CER 0805 CHIP 100P 5% NPO 50V	C320		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C209		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	C321		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V
C210		015-23100-01	CAP CER 0805 CHIP 100P 5% NPO 50V	C322		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V
C211		015-22560-01	CAP CER 0805 CHIP 56P 5% NPO 50V	C324		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V
CV212		028-02200-01	CAP TRIM 4/20P N750 TOP ADJ RED MUR TZ	C325		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V

Ref	Var	IPN	Description	Ref	Var	IPN	Description
C326		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L1		030-50000-00	LINK WIRE AI ZERO OHM 0.6MM WIRE
C328		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	L107		050-10061-70	BALUN MIXER SMD 617DB-1018
C329		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L108		050-10061-70	BALUN MIXER SMD 617DB-1018
C330		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L110		056-00021-60	IND FXD 330NH 6.6X2.7MM AXIAL NON MAGNET
C331		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L114		050-00016-62	COIL IF 1UH AT 30MHZ 6MMSQX6.2MMH CAN 29
C332		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L116		050-00016-62	COIL IF 1UH AT 30MHZ 6MMSQX6.2MMH CAN 29
C333		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L117		050-00016-65	COIL BALUN 7.2MM2 5X0.5PINS 5T/4 456DB-1
C334		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L118		050-00016-65	COIL BALUN 7.2MM2 5X0.5PINS 5T/4 456DB-1
C335		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L119		050-00016-55	COIL TAIT NO 655 455KHZ QUAD COIL 7MM CA
C336		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L120		057-10005-03	IND 0805 BLM21B05 EMI SUPRSN 5 OHM AT 10
C337		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L121		057-10120-03	IND 0805 BLM21A121 EMI SUPRSN 120 OHM @
C338		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L200		057-10005-03	IND 0805 BLM21B05 EMI SUPRSN 5 OHM AT 10
C339		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L201		057-00100-00	IND FXD SMD 100NH 10% 2.5X3.5MM MUR LQN2
C340		015-02330-06	CAP CER 1210 CHIP 33P NPO 500V GRM42-2	L202		056-10820-00	IND FXD SMD 820NH 3.2*2.5*1.6 SIEMENS SM
C341		015-01270-06	CAP CER 1210 CHIP 2P7 NPO 200V GRM42-2	L204		050-00016-62	COIL IF 1UH AT 30MHZ 6MMSQX6.2MMH CAN 29
C342		015-21100-01	CAP CER 0805 CHIP 1PO +/-0.25P NPO 50V	L205		056-10330-00	IND FXD SMD 330NH 3.2*2.5*1.6 SIEMENS SM
C343		015-01330-06	CAP CER 1210 CHIP 3P3 NPO 500V GRM42-2	L206		056-10330-00	IND FXD SMD 330NH 3.2*2.5*1.6 SIEMENS SM
C344		015-01330-06	CAP CER 1210 CHIP 3P3 NPO 500V GRM42-2	L207		051-00616-00	COAX RES 28MM (STRIPPED) X 2.18MM T2000
C345		015-21100-01	CAP CER 0805 CHIP 1PO +/-0.25P NPO 50V	L208		056-10330-00	IND FXD SMD 330NH 3.2*2.5*1.6 SIEMENS SM
C346		015-01270-06	CAP CER 1210 CHIP 2P7 NPO 200V GRM42-2	L209		056-10330-00	IND FXD SMD 330NH 3.2*2.5*1.6 SIEMENS SM
C347		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L211		056-10100-00	IND FXD SMD 100NH 3.2*2.5*1.6 SIEMENS SM
C348		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L213		056-10100-00	IND FXD SMD 100NH 3.2*2.5*1.6 SIEMENS SM
C349		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L214		056-10330-00	IND FXD SMD 330NH 3.2*2.5*1.6 SIEMENS SM
C350		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L300		056-10330-00	IND FXD SMD 330NH 3.2*2.5*1.6 SIEMENS SM
C351		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	L302		056-10330-00	IND FXD SMD 330NH 3.2*2.5*1.6 SIEMENS SM
C352		015-02330-06	CAP CER 1210 CHIP 33P NPO 500V GRM42-2	L304		057-10005-03	IND 0805 BLM21B05 EMI SUPRSN 5 OHM AT 10
C353		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	L306		057-10005-03	IND 0805 BLM21B05 EMI SUPRSN 5 OHM AT 10
C354		022-06330-03	CAP METAL POLYES 330N 10% 50V 5MM L/S	L308		052-56130-85	COIL A/W 8.5T/3.0MM HOR 0.56MM WIRE
C355		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L309		057-00015-00	IND FXD 15NH +/-5% 1206 CHIP MUR LQN1A15N
C356		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	L311		052-56130-85	COIL A/W 8.5T/3.0MM HOR 0.56MM WIRE
C357		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	L312		056-00021-60	IND FXD 330NH 6.6X2.7MM AXIAL NON MAGNET
C358		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	L313		052-08330-10	COIL A/W 1T/3.0MM SMD 0.8MM WIRE
C359		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	L315		052-08130-25	COIL A/W 2.5T/3.0MM HOR 0.8MM WIRE
C360		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L316		052-56130-85	COIL A/W 8.5T/3.0MM HOR 0.56MM WIRE
C361		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	L317		052-56130-85	COIL A/W 8.5T/3.0MM HOR 0.56MM WIRE
C362		020-57100-55	CAP ELECT AI RDL 1UF 50V 4X7MM	L318		052-56130-85	COIL A/W 8.5T/3.0MM HOR 0.56MM WIRE
C363		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	L319		052-56130-85	COIL A/W 8.5T/3.0MM HOR 0.56MM WIRE
C364		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	L320		052-08130-35	COIL A/W 3.5T/3.0MM HOR 0.8MM WIRE
C365		020-57100-55	CAP ELECT AI RDL 1UF 50V 4X7MM	L321		052-56130-85	COIL A/W 8.5T/3.0MM HOR 0.56MM WIRE
C366		015-22330-01	CAP CER 0805 CHIP 33P 5% NPO 50V	L322		052-08340-10	COIL A/W 1T/4.0MM SMD 0.8MM WIRE
C367		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	L323		052-08345-10	COIL A/W 1T/4.5MM SMD 0.8MM WIRE
C403		015-23470-08	CAP CER 0805 CHIP 470P 10% X7R 50V	L324		052-08335-10	COIL A/W 1T/3.5MM SMD 0.8MM WIRE
C410		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR	L325		030-50000-00	LINK WIRE AI ZERO OHM 0.6MM WIRE
C411		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	L326		030-50000-00	LINK WIRE AI ZERO OHM 0.6MM WIRE
C412		020-58470-05	CAP ELECT AI RDL 47M 16V 6.3X7MM	L327		057-10005-03	IND 0805 BLM21B05 EMI SUPRSN 5 OHM AT 10
C413		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	L331		057-10005-03	IND 0805 BLM21B05 EMI SUPRSN 5 OHM AT 10
C414		020-09470-05	CAP ELECT RADL 470M 16V 10X12.5MM	L401		050-00016-50	COIL TAIT NO 650 455KHZ 5.6MM CAN
C415		020-19100-02	CAP ELECT RADL 1000M 16V 12X20MM				
C416		015-23470-08	CAP CER 0805 CHIP 470P 10% X7R 50V	P1		240-00026-24	CONN PADLE BRD 16 WAY MICRO MATCH 1-2155
C419		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	P2		240-00026-26	CONN PADLE BRD 12 WAY MICRO MATCH 1-2155
C420		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	P3		240-00026-21	PLUG CAP HOUSING 7-POS CONN 172039-1
C423		020-08560-09	CAP ELECT RADL 56M 50V 6.3X15.5MM L/S	P5		240-00010-76	PLUG HEADER 10WAY MICROMATCH PCB MTD 1-
C424		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR	P6		240-00010-76	PLUG HEADER 10WAY MICROMATCH PCB MTD 1-
C425		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR	P7		240-00020-72	HEADER 2 WAY PCB MTG ULTREX
C426		015-25100-08	CAP CER 0805 CHIP 10N 10% X7R 50V				
C427		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR	Q101		000-10052-00	(LS) XSTR SMD BFG520/X 9GHZ RF SML SIG N
C428		020-57470-10	CAP ELECT AI RDL 4U7 50V LO ESR	Q102		000-10008-57	(S) XSTR SMD BCW70 PNP SOT23 AF SML SIG
C429		015-24100-08	CAP CER 0805 CHIP 1N 10% X7R 50V	Q103		000-10095-10	(S) XSTR SMD MMBR951 NPN UHF SOT-23
C430		020-08560-09	CAP ELECT RADL 56M 50V 6.3X15.5MM L/S	Q115		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
C431		015-06100-08	CAP CER 1206 CHIP 100N 10% X7R 50V	Q200		000-10003-10	(S) XSTR SMD MMBFJ310 JFET SOT-23 UHF
				Q201		000-10008-57	(S) XSTR SMD BCW70 PNP SOT23 AF SML SIG
				Q202		000-10003-10	(S) XSTR SMD MMBFJ310 JFET SOT-23 UHF
				Q203		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q204		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q205		000-10008-57	(S) XSTR SMD BCW70 PNP SOT23 AF SML SIG
				Q206		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q207		000-10008-57	(S) XSTR SMD BCW70 PNP SOT23 AF SML SIG
				Q208		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q209		000-10008-57	(S) XSTR SMD BCW70 PNP SOT23 AF SML SIG
				Q210		000-10003-12	(S) XSTR SMD BFR31 N JFET SOT-23
				Q211		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q212		000-10009-41	(S) XSTR SMD MMBR941L RF LOW NOISE SOT23
				Q213		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q214		000-10009-41	(S) XSTR SMD MMBR941L RF LOW NOISE SOT23
				Q215		000-10057-10	(S) XSTR SMD MMBR571 NPN SOT-23 UHF LO P
				Q300		000-10095-10	(S) XSTR SMD MMBR951 NPN UHF SOT-23
				Q301		000-10095-10	(S) XSTR SMD MMBR951 NPN UHF SOT-23
				Q302		000-00032-47	(S) XSTR MRF559 NPN XPACK UHF PWR 0.5W
				Q303		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q304		000-00012-15	(S) XSTR BD234 PNP AF PWR TO126
				Q305		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q306		000-10008-07	(S) XSTR SMD BC807 PNP SOT-23 AF LO PWR
				Q307		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q308		000-10008-07	(S) XSTR SMD BC807 PNP SOT-23 AF LO PWR
				Q309		000-10008-48	(S) XSTR SMD BCW60/BC848B215 NPN SOT23 A
				Q401		000-10008-57	(S) XSTR SMD BCW70 PNP SOT23 AF SML SIG
D1		001-00012-90	(S) DIODE MR2520L OVERVOLT SUPPRESSOR				
D100		001-10000-99	(S) DIODE SMD BAV99 DUAL SWITCH SINGLE INL				
D107		001-10000-17	(S) DIODE SMD DUAL BAT-17 SCHOTTKY SML S				
D108		001-10000-17	(S) DIODE SMD DUAL BAT-17 SCHOTTKY SML S				
D110		001-10014-00	(LS) DIODE SMD BAT14-099R QUAD CRSSD SCH				
D202		001-10000-70	(S) DIODE SMD BAV70 DUAL SWITCH SOT-23 C				
D203		001-10005-35	(S) DIODE SMD VARICAP BB535 SOD323				
D204		001-10005-35	(S) DIODE SMD VARICAP BB535 SOD323				
D205		001-10005-35	(S) DIODE SMD VARICAP BB535 SOD323				
D206		001-10005-35	(S) DIODE SMD VARICAP BB535 SOD323				
D208		001-10014-01	(LS) DIODE SMD BAR14-1 DUAL SI PIN SOT-2				
D301		001-00013-45	(S) DIODE SCHOTTKY 1SS97/2				
D302		001-00012-50	(S) DIODE PIN UM9401 UHF PWR SWITCH				
D303		001-00012-50	(S) DIODE PIN UM9401 UHF PWR SWITCH				
D304		001-00010-26	(S) DIODE BA482 RF SWITCH				
D401		001-10000-70	(S) DIODE SMD BAV70 DUAL SWITCH SOT-23 C				
IC101		002-10033-71	(S) IC SMD MC3371D-R2 FM IF DETECT RSSI				
IC201		002-10451-58	(S) IC SMD MC145158DW2 FREQ SYNTH SOIC				
IC202		002-10330-78	(S) IC MC33078D-R2 DUAL AMP LO NOISE SO				
IC203		002-10120-22	(S) IC SMD MC12022AD-R2 PRESC 8-P				
IC402		002-00013-70	(S) IC TDA1020 AF PWR AMP 9PIN SIL				
IC403		002-00078-08	(S) IC MC7808ACT 8V REG(LINEAR)1AMP TO-				
IC404		002-00078-05	(S) IC MC7805ACT 5V REG(LINEAR)1AMP TO-				
IC405		004-00070-73	(L) MODULE RF PWR MHW820-1 806-870MHZ 2				