



ISSUE B
DRG No WAS
08-04124 SHT 3
C/R 22892
12-8-91 MB

ISSUE C
NOTES & PARTS
LIST ADDED.
C/R 23035 AMJ
3-9-91

ISSUE 2
NOTE 6 WAS 5,
NEW NOTE 5 ADDED,
ITEM 3 WAS
08-04286.
C/R 23651

ISSUE 3
NOTE 1 CHANGED,
C201 ETC ADDED,
REG BD WIRING
CHANGED.
C/R 23774 CM
13-10-93

ISSUE 4
ITEMS 6 & 7
ADDED.
C/R 23798
lu 1-10-94

NOTES

1. REMOVE 4 SCREWS SECURING CONSOLE TOP TO CHASSIS. DISCONNECT WIRING FROM CONNECTORS P1 & P7 ON AUDIO PROCESSING PCB, P3 ON MICROCONTROLLER & DISPLAY PCB AND INTERCONNECTING EARTHING WIRE ENABLING TOP COVER TO BE SEPARATED FROM CHASSIS. REMOVE CAPACITOR C201 & CLAMP, DIODES D201 & D202 AND ASSOCIATED WIRING IF FITTED.
2. PLACE BATTERY IN POSITION ON CHASSIS, SECURE IN PLACE WITH BATTERY RETAINING BRACKET & BATTERY CLAMP
3. FIT BATTERY CHARGE REGULATOR PCB ASSEMBLY ITEM 3 TO CHASSIS.
4. CONNECT RED/BLACK POWER CABLE FROM REGULATOR TO BATTERY, TRANSFORMER CABLE TO REGULATOR AND REGULATED OUTPUT CABLE TO P3 ON AUDIO PROCESSING PCB.
5. IF P3 IS NOT COMPATIBLE WITH FITTED CABLE, CHANGE TO OPTIONAL CABLE (08-04287) SUPPLIED.
6. REPLACE CABLES FROM MICROCONTROLLER & DISPLAY PCB, SECURE CONSOLE TOP TO CHASSIS WITH 4 SCREWS.

PARTS LIST

ITEM	PART No	DESCRIPTION
-	15-10379-001	FITTING INSTRUCTIONS
-	08-04287	LOOM OPT SB (REF NOTE 5)
1	08-04104	BATTERY CLAMP
2	08-04150	BATTERY RETAINING BRACKET
3	08-05022	BATTERY CHARGE REGULATOR
4	65-72000-010	BATTERY, 12V 1.3Ah LEAD ACID
5	31-23006-582	SCREW, M3 x 6
6	31-23000-080	NUT, M3
7	31-23001-001	WASHER, M3

OPTION SB - 15-10379-000

DISC FILE

	SCALE FULL		TITLE REMOTE CONTROL CONSOLE, 8570 OPTION SB
	DRN	DB	
MATERIAL	CHKD	RM	3-7-90
	APPD	NJA	12-11-91
FINISH	TOLERANCES UNLESS OTHERWISE STATED		DRAWING/DOC NO. A2 15-10379-001
	2 PLACES DEC. ±		
1 PLACE DEC. ±		ISS	SHT 1 OF 1
ANGULAR ±		3 4	