



Parts List for the Tait Orca H Band PCB (400 to 470 MHz)

Product Code: OPMH20-T, Rev. 25

PCB IPN: 220-01603-10

Ref	IPN	Description	Ref	IPN	Description
+SPKR	356-01070-00	Spring Spkr Cntct Probe	C171	018-14100-00	Cap 0603 1n 50v X7r +-10%
-SPKR	356-01070-00	Spring Spkr Cntct Probe	C172	015-21390-05	Cap Cer 0805 3p9+0.1pf 200v
AUDIO	319-01212-00	Shld Audio T/Orca	C173	015-21270-05	Cap Cer 0805 2p7 +0.1pf 200v
BATTERY+	356-01070-00	Spring Spkr Cntct Probe	C2	018-15470-00	Cap 0603 47n 16v X7r+-10%
BATTERY-	356-01070-00	Spring Spkr Cntct Probe	C200	018-14100-00	Cap 0603 1n 50v X7r +-10%
BL301	050-10061-70	Bal Mxr SMD 617db-1018	C202	018-16100-00	Cap 0603 100n 16vx7r+-10%
BL302	050-10061-70	Bal Mxr SMD 617db-1018	C208	015-07470-08	Cap 1206 4u7 -20%+80% Y5v 16v
C1	018-16100-00	Cap 0603 100n 16vx7r+-10%	C209	018-16100-00	Cap 0603 100n 16vx7r+-10%
C10	018-15100-00	Cap 0603 10n 50v X7r +-10%	C210	018-16100-00	Cap 0603 100n 16vx7r+-10%
C100	018-13150-00	Cap 0603 150p 50v NPO +5%	C211	018-16100-00	Cap 0603 100n 16vx7r+-10%
C101	018-14100-00	Cap 0603 1n 50v X7r +-10%	C212	018-14100-00	Cap 0603 1n 50v X7r +-10%
C102	018-12150-10	Cap 0603 15p 50v NPO +-1%	C213	018-14100-00	Cap 0603 1n 50v X7r +-10%
C103	018-14100-00	Cap 0603 1n 50v X7r +-10%	C214	018-13150-00	Cap 0603 150p 50v NPO +5%
C104	018-16100-00	Cap 0603 100n 16vx7r+-10%	C215	018-13150-00	Cap 0603 150p 50v NPO +5%
C105	018-14100-00	Cap 0603 1n 50v X7r +-10%	C216	018-13150-00	Cap 0603 150p 50v NPO +5%
C106	018-14100-00	Cap 0603 1n 50v X7r +-10%	C217	018-15100-00	Cap 0603 10n 50v X7r +-10%
C11	018-15100-00	Cap 0603 10n 50v X7r +-10%	C218	014-07100-02	Cap Tant SMD 1u0 16v 20% A
C110	018-12100-10	Cap 0603 10p 50v NPO+0.1	C219	013-06330-01	Cap 330n 16v 6*4mm
C111	018-12270-10	Cap 0603 27p 50v NPO +-1%	C220	018-15100-00	Cap 0603 10n 50v X7r +-10%
C112	018-15100-00	Cap 0603 10n 50v X7r +-10%	C222	013-06100-01	Cap 100n 5% 63v Cf 1812
C113	018-15100-00	Cap 0603 10n 50v X7r +-10%	C223	018-13470-00	Cap 0603 470p 50v X7r+-10%
C114	018-16100-00	Cap 0603 100n 16vx7r+-10%	C226	018-16100-00	Cap 0603 100n 16vx7r+-10%
C115	018-15100-00	Cap 0603 10n 50v X7r +-10%	C229	018-14100-00	Cap 0603 1n 50v X7r +-10%
C116	018-13100-00	Cap 0603 100p 50v NPO +5%	C240	018-16100-00	Cap 0603 100n 16vx7r+-10%
C117	018-12470-10	Cap 0603 47p 50v NPO+0.1	C241	018-15100-00	Cap 0603 10n 50v X7r +-10%
C120	015-23470-08	Cap Cer 0805 470p 10% X7r 50v	C242	015-07470-08	Cap 1206 4u7 -20%+80% Y5v 16v
C121	018-16100-00	Cap 0603 100n 16vx7r+-10%	C246	018-14100-00	Cap 0603 1n 50v X7r +-10%
C122	018-15100-00	Cap 0603 10n 50v X7r +-10%	C247	014-07470-05	Cap Tant SMD 4u7 16v 10% A
C123	015-22330-05	Cap Cer 0805 33p+-0.1pf 200v	C270	018-16100-00	Cap 0603 100n 16vx7r+-10%
C124	015-22390-05	Cap 0805 39p 1% 200v	C271	018-16100-00	Cap 0603 100n 16vx7r+-10%
C125	018-16100-00	Cap 0603 100n 16vx7r+-10%	C272	018-16100-00	Cap 0603 100n 16vx7r+-10%
C126	018-14100-00	Cap 0603 1n 50v X7r +-10%	C273	018-15100-00	Cap 0603 10n 50v X7r +-10%
C130	015-07470-08	Cap 1206 4u7 -20%+80% Y5v 16v	C274	018-15100-00	Cap 0603 10n 50v X7r +-10%
C131	018-15100-00	Cap 0603 10n 50v X7r +-10%	C275	018-13150-00	Cap 0603 150p 50v NPO +5%
C132	018-15100-00	Cap 0603 10n 50v X7r +-10%	C276	018-16100-00	Cap 0603 100n 16vx7r+-10%
C133	015-23150-01	Cap Cer 0805 150p 5% NPO 50v	C278	018-13150-00	Cap 0603 150p 50v NPO +5%
C135	015-22270-05	Cap Cer 0805 27p+-0.1pf 200v	C279	018-16100-00	Cap 0603 100n 16vx7r+-10%
C136	018-15100-00	Cap 0603 10n 50v X7r +-10%	C280	015-07220-08	Cap 1206 2u2 16v X7r
C137	015-22120-05	Cap 0805 12p 1% NPO 200v	C3	018-16100-00	Cap 0603 100n 16vx7r+-10%
C138	015-22150-05	Cap 0805 15p 1% 200v	C300	018-13100-00	Cap 0603 100p 50v NPO +5%
C140	018-16100-00	Cap 0603 100n 16vx7r+-10%	C301	018-11470-10	Cap 0603 4p7 50v NPO+0.1p
C141	015-22270-05	Cap Cer 0805 27p+-0.1pf 200v	C302	018-11470-10	Cap 0603 4p7 50v NPO+0.1p
C143	018-11330-10	Cap 0603 3p3 50v NPO+0.1p	C303	018-11330-10	Cap 0603 3p3 50v NPO+0.1p
C144	015-21820-05	Cap Cer 0805 8p2+-0.1pf 200v	C304	018-12270-10	Cap 0603 27p 50v NPO +1%
C145	015-21330-05	Cap Cer 0805 3p3+-0.1pf 200v	C305	018-11390-10	Cap 0603 3p9 50v NPO+0.1p
C146	018-15100-00	Cap 0603 10n 50v X7r +-10%	C306	018-11470-10	Cap 0603 4p7 50v NPO+0.1p
C147	018-15270-00	Cap 0603 27n 50v X7r+-10%	C309	018-15100-00	Cap 0603 10n 50v X7r +-10%
C15	018-14100-00	Cap 0603 1n 50v X7r +-10%	C310	018-13150-00	Cap 0603 150p 50v NPO +5%
C150	018-13100-10	Cap 0603 100p 50v NPO+-1%	C311	018-14100-00	Cap 0603 1n 50v X7r +-10%
C151	015-22100-05	Cap Cer 0805 10p +0.1pf 200v	C312	018-14100-00	Cap 0603 1n 50v X7r +-10%
C152	015-07470-08	Cap 1206 4u7 -20%+80% Y5v 16v	C315	018-11330-10	Cap 0603 3p3 50v NPO+0.1p
C153	015-21820-05	Cap Cer 0805 8p2+-0.1pf 200v	C316	018-11470-10	Cap 0603 4p7 50v NPO+0.1p
C154	018-15100-00	Cap 0603 10n 50v X7r +-10%	C317	018-11680-10	Cap 0603 6p8 50v NPO+0.1p
C155	018-13100-00	Cap 0603 100p 50v NPO +5%	C318	018-12270-10	Cap 0603 27p 50v NPO +-1%
C156	018-15100-00	Cap 0603 10n 50v X7r +-10%	C319	018-11180-10	Cap 0603 1p8 50v NPO+0.1p
C157	018-12560-10	Cap 0603 56p 50v NPO +-1%	C320	018-11270-10	Cap 0603 2p7 50v NPO+0.1p
C16	018-13150-00	Cap 0603 150p 50v NPO +5%	C325	018-15100-00	Cap 0603 10n 50v X7r +-10%
C160	015-23100-01	Cap Cer 0805 100p 5% NPO 50v	C326	018-11330-10	Cap 0603 3p3 50v NPO+0.1p
C161	018-14100-00	Cap 0603 1n 50v X7r +-10%	C326A	018-11390-10	Cap 0603 3p9 50v NPO+0.1p
C162	015-21330-05	Cap Cer 0805 3p3+-0.1pf 200v	C327	018-12270-10	Cap 0603 27p 50v NPO +-1%
C163	018-16100-00	Cap 0603 100n 16vx7r+-10%	C328	018-11270-10	Cap 0603 2p7 50v NPO+0.1p
C164	015-21470-05	Cap Cer 0805 4p7+-0.1pf 200v	C329	018-11330-10	Cap 0603 3p3 50v NPO+0.1p
C165	015-21470-05	Cap Cer 0805 4p7+-0.1pf 200v	C331	018-12120-10	Cap 0603 12p 50v NPO +-1%
C166	015-21330-05	Cap Cer 0805 3p3+-0.1pf 200v	C333	018-15100-00	Cap 0603 10n 50v X7r +-10%
C170	015-21470-05	Cap Cer 0805 4p7+-0.1pf 200v	C334	018-15100-00	Cap 0603 10n 50v X7r +-10%
			C335	018-12150-10	Cap 0603 15p 50v NPO +-1%
			C336	018-11100-10	Cap 0603 1p0 50v NPO+0.1p
			C337	018-15100-00	Cap 0603 10n 50v X7r +-10%

Parts List for the Tait Orca H Band PCB (400 to 470 MHz)

Ref	IPN	Description	Ref	IPN	Description
C338	018-15100-00	Cap 0603 10n 50v X7r +-10%	C551	018-16100-00	Cap 0603 100n 16vx7r+-10%
C339	018-15100-00	Cap 0603 10n 50v X7r +-10%	C553	014-18100-05	Cap Tant SMD 10u 10v 10% A
C340	018-15100-00	Cap 0603 10n 50v X7r +-10%	C559	018-14100-00	Cap 0603 1n 50v X7r +-10%
C342	018-12470-10	Cap 0603 47p 50v NPO+-0.1	C560	015-23470-08	Cap Cer 0805 470p 10% X7r 50v
C343	018-12180-10	Cap 0603 18p 50v NPO +-1%	C561	018-16100-00	Cap 0603 100n 16vx7r+-10%
C344	018-12220-10	Cap 0603 22p 50v NPO+-0.1	C566	018-13390-00	Cap 0603 390p 50v X7r+-10%
C345	018-12100-10	Cap 0603 10p 50v NPO+-0.1	C567	015-26220-08	Cap 0805 220n 10% X7r 16v
C346	018-13100-10	Cap 0603 100p 50v NPO+-1%	C568	018-14100-00	Cap 0603 1n 50v X7r +-10%
C350	018-15100-00	Cap 0603 10n 50v X7r +-10%	C569	018-15270-00	Cap 0603 27n 50v X7r+-10%
C351	018-12150-10	Cap 0603 15p 50v NPO +-1%	C571	018-15470-00	Cap 0603 47n 16v X7r+-10%
C352	018-12330-10	Cap 0603 33p 50v NPO +-1%	C572	015-26100-08	Cap Cer 0805 100n 10% X7r 50v
C355	018-14100-00	Cap 0603 1n 50v X7r +-10%	C573	018-16100-00	Cap 0603 100n 16vx7r+-10%
C356	018-16100-00	Cap 0603 100n 16vx7r+-10%	C574	018-15470-00	Cap 0603 47n 16v X7r+-10%
C357	018-16100-00	Cap 0603 100n 16vx7r+-10%	C576	015-27100-10	Cap Cer 0805 1m+80-20% Y5v 16v
C358	018-16100-00	Cap 0603 100n 16vx7r+-10%	C578	015-26220-08	Cap 0805 220n 10% X7r 16v
C359	018-16100-00	Cap 0603 100n 16vx7r+-10%	C579	036-00000-00	Res 1206 0e 5% 0.125w
C360	018-16100-00	Cap 0603 100n 16vx7r+-10%	C581	018-15470-00	Cap 0603 47n 16v X7r+-10%
C362	018-16100-00	Cap 0603 100n 16vx7r+-10%	C582	018-15470-00	Cap 0603 47n 16v X7r+-10%
C363	015-07470-08	Cap 1206 4u7 -20%+80% Y5v 16v	C583	015-27100-10	Cap Cer 0805 1m+80-20% Y5v 16v
C364	014-07100-02	Cap Tant SMD 1u0 16v 20% A	C588	015-07470-08	Cap 1206 4u7 -20%+80% Y5v 16v
C365	018-16100-00	Cap 0603 100n 16vx7r+-10%	C590	018-16100-00	Cap 0603 100n 16vx7r+-10%
C366	018-14100-00	Cap 0603 1n 50v X7r +-10%	C593	015-27100-10	Cap Cer 0805 1m+80-20% Y5v 16v
C367	018-13180-00	Cap 0603 180p 50v NPO+-5%	C594	014-07100-02	Cap Tant SMD 1u0 16v 20% A
C368	018-13180-00	Cap 0603 180p 50v NPO+-5%	C595	015-26220-08	Cap 0805 220n 10% X7r 16v
C369	018-13470-00	Cap 0603 470p 50v X7r+-10%	C596	015-26220-08	Cap 0805 220n 10% X7r 16v
C370	018-12220-10	Cap 0603 22p 50v NPO+-0.1	C597	018-16100-00	Cap 0603 100n 16vx7r+-10%
C372	018-12330-10	Cap 0603 33p 50v NPO +-1%	C6	018-15100-00	Cap 0603 10n 50v X7r +-10%
C375	015-07470-08	Cap 1206 4u7 -20%+80% Y5v 16v	C608	014-07470-05	Cap Tant SMD 4u7 16v 10% A
C376	014-07100-02	Cap Tant SMD 1u0 16v 20% A	C610	018-15100-00	Cap 0603 10n 50v X7r +-10%
C378	018-15100-00	Cap 0603 10n 50v X7r +-10%	C612	018-12390-10	Cap 0603 39p 50v NPO +-1%
C379	018-15100-00	Cap 0603 10n 50v X7r +-10%	C614	018-11270-10	Cap 0603 2p7 50v NPO+-0.1p
C384	018-15100-00	Cap 0603 10n 50v X7r +-10%	C616	018-14100-00	Cap 0603 1n 50v X7r +-10%
C385	018-16100-00	Cap 0603 100n 16vx7r+-10%	C618	018-14100-00	Cap 0603 1n 50v X7r +-10%
C4	018-14100-00	Cap 0603 1n 50v X7r +-10%	C619	018-13150-00	Cap 0603 150p 50v NPO +-5%
C400	018-12120-10	Cap 0603 12p 50v NPO +-1%	C640	018-15100-00	Cap 0603 10n 50v X7r +-10%
C401	018-11560-10	Cap 0603 5p6 50v NPO+-0.1p	C7	018-15100-00	Cap 0603 10n 50v X7r +-10%
C402	018-11330-10	Cap 0603 3p3 50v NPO+-0.1p	C8	018-15100-00	Cap 0603 10n 50v X7r +-10%
C404	018-11470-10	Cap 0603 4p7 50v NPO+-0.1p	C9	018-15100-00	Cap 0603 10n 50v X7r +-10%
C406	018-13150-00	Cap 0603 150p 50v NPO +-5%			
C408	018-13150-00	Cap 0603 150p 50v NPO +-5%	D1	008-10000-20	LED SMD Red/Grn Sml-020
C410	018-11820-10	Cap 0603 8p2 50v NPO+-0.1p	D103	001-10012-50	Diode SMD MA4P1250 Pin3x2mm
C412	018-13150-00	Cap 0603 150p 50v NPO +-5%	D105	001-10065-02	Diode SMD BAP65-02 Pin SOD523
C413	018-16100-00	Cap 0603 100n 16vx7r+-10%	D106	001-10065-02	Diode SMD BAP65-02 Pin SOD523
C416	018-15100-00	Cap 0603 10n 50v X7r +-10%	D107	001-10065-02	Diode SMD BAP65-02 Pin SOD523
C417	018-11100-10	Cap 0603 1p0 50v NPO+-0.1p	D205	001-10099-01	Diode BAV99w Dual Ss
C418	018-11120-10	Cap 0603 1p2 50v NPO+-0.1p	D206	001-10099-01	Diode BAV99w Dual Ss
C419	018-11600-10	Cap 0603 6p0 50v NPO+-0.1p	D270	001-10099-01	Diode BAV99w Dual Ss
C422	018-13150-00	Cap 0603 150p 50v NPO +-5%	D301	001-10043-90	Diode SMD BB439 Vcap SOD323
C423	018-13150-00	Cap 0603 150p 50v NPO +-5%	D302	001-10043-90	Diode SMD BB439 Vcap SOD323
C424	018-13150-00	Cap 0603 150p 50v NPO +-5%	D303	001-10043-90	Diode SMD BB439 Vcap SOD323
C426	018-13150-00	Cap 0603 150p 50v NPO +-5%	D304	001-10099-01	Diode BAV99w Dual Ss
C430	018-11820-10	Cap 0603 8p2 50v NPO+-0.1p	D305	001-10015-00	Diode SMD BAT15-099R Sch
C431	018-11600-10	Cap 0603 6p0 50v NPO+-0.1p	D400	001-10043-90	Diode SMD BB439 Vcap SOD323
C432	018-13150-00	Cap 0603 150p 50v NPO +-5%	D402	001-10043-90	Diode SMD BB439 Vcap SOD323
C436	018-11150-10	Cap 0603 1p5 50v NPO+-0.1p	D404	001-10043-90	Diode SMD BB439 Vcap SOD323
C437	018-11050-00	Cap 0603 0p5 50v NPO+-0.25p	D406	001-10043-90	Diode SMD BB439 Vcap SOD323
C439	018-16100-00	Cap 0603 100n 16vx7r+-10%	D502	001-10056-01	Diode BAW56W Dual Ss SOT323
C440	018-15100-00	Cap 0603 10n 50v X7r +-10%	D504	001-10000-70	Diode SMD BAV70 D-Sw SOT23
C442	018-13150-00	Cap 0603 150p 50v NPO +-5%	D506	001-10099-01	Diode BAV99w Dual Ss
C446	018-13150-00	Cap 0603 150p 50v NPO +-5%	D507	001-10099-01	Diode BAV99w Dual Ss
C5	018-15100-00	Cap 0603 10n 50v X7r +-10%	D508	001-10056-01	Diode BAW56W Dual Ss SOT323
C502	018-16100-00	Cap 0603 100n 16vx7r+-10%	D510	001-10099-01	Diode BAV99w Dual Ss
C504	018-16100-00	Cap 0603 100n 16vx7r+-10%			
C505	018-16100-00	Cap 0603 100n 16vx7r+-10%	DIG	319-01216-01	Shld Ctrl T/Orca
C506	018-16100-00	Cap 0603 100n 16vx7r+-10%			
C506A	018-13150-00	Cap 0603 150p 50v NPO +-5%	FUNC-1	232-00010-32	Sw Tact Nonlatch Skqtlta Pcb
C512	018-12100-10	Cap 0603 10p 50v NPO+-0.1	FUNC-2	232-00010-32	Sw Tact Nonlatch Skqtlta Pcb
C514	018-12470-10	Cap 0603 47p 50v NPO+-0.1			
C515	018-12470-10	Cap 0603 47p 50v NPO+-0.1	IC100	002-10139-16	IC MBC13916 Cascade Buffer
C516	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC101	002-10003-58	IC SMD LM358 Dual 0-Amp
C518	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC104	002-11125-00	IC TK11250 5vreg 130ma
C520	018-14100-00	Cap 0603 1n 50v X7r +-10%	IC201	002-12347-00	IC PMB2347 PLL20 Pin SMD
C524	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC202	002-11125-01	IC TK11250 Bmcl 5vreg 130ma
C525	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC203	002-10227-20	IC SMD TLC2272CD 0-Amp
C528	018-15100-00	Cap 0603 10n 50v X7r +-10%	IC301	002-11315-00	IC MC13150 Fm If Detector
C530	015-07470-08	Cap 1206 4u7 -20%+80% Y5v 16v	IC302	002-20103-24	IC BA10324 4x Op Amp Ssop-14
C532	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC400	002-10139-16	IC MBC13916 Cascade Buffer
C534	018-15100-00	Cap 0603 10n 50v X7r +-10%	IC402	002-10139-16	IC MBC13916 Cascade Buffer
C535	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC501	002-11810-50	IC DS1810R-5 5V 5% Mup Reset
C536	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC502	002-10681-11	IC MC68HC11E1CFU3 Micrtrlr
C540	018-15100-00	Cap 0603 10n 50v X7r +-10%	IC503	002-30000-11	ASlc Comm Pllfrm Dgtl Ntrl
C542	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC504	002-12902-00	IC 29EE020 Flash 120ns Tsop
C543	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC506	002-11125-00	IC TK11250 5vreg 130ma
C544	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC507	002-10126-71	IC SMD DS1868 Dgtl Pot Tsop20
C545	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC508	002-16235-40	IC SMD M62354GP 8b 6cml D-A
C548	014-18100-05	Cap Tant SMD 10u 10v 10% A	IC509	002-18937-17	IC SMD Z8937 V3.21 Prog Otp
C549	015-27100-10	Cap Cer 0805 1m+80-20% Y5v 16v	IC510	002-11454-80	IC SMD MC145480DW Pcm
C550	018-16100-00	Cap 0603 100n 16vx7r+-10%	IC511	002-10003-24	IC SMD 324 4x 0-Amp S014

Parts List for the Tait Orca H Band PCB (400 to 470 MHz)

Ref	IPN	Description	Ref	IPN	Description
IC512	002-10854-10	IC TDA8541T 1w Audio Amp	Q505	000-10084-71	Xstr BC847BW NPN SOT323
IC513	002-10040-53	IC SMD 4053B Break B4 Make	Q506	000-10084-71	Xstr BC847BW NPN SOT323
IC514	002-10021-00	IC PHN210 Dual Nch En Mfet	Q513	000-10084-71	Xstr BC847BW NPN SOT323
IC515	002-10003-21	IC SMD LMV321 Sngle Op Amp	Q514	000-10084-71	Xstr BC847BW NPN SOT323
INTER	240-02010-93	Conn 22w Ffc Molex Ra SMD	Q516	000-10085-71	Xstr SMD BC857BW PNP SOT323
L101	059-15560-00	Ind SMD 0603hs 56nh 5%	Q517	000-10085-71	Xstr SMD BC857BW PNP SOT323
L102	057-11220-02	Ind 0603 Blm11a221 Emi Supr	Q518	000-10084-71	Xstr BC847BW NPN SOT323
L103	057-11220-02	Ind 0603 Blm11a221 Emi Supr	Q519	000-10084-71	Xstr BC847BW NPN SOT323
L104	057-11220-02	Ind 0603 Blm11a221 Emi Supr	Q522	000-10084-71	Xstr BC847BW NPN SOT323
L105	059-15120-00	Ind SMD 0603hs 12nh 5%	Q524	000-10084-71	Xstr BC847BW NPN SOT323
L110	059-15047-00	Ind SMD 0603cs 4n7xj	Q527	000-10084-71	Xstr BC847BW NPN SOT323
L111	057-10080-06	Ind Blm41-P800 1a 180hm 100MHz	Q529	000-10085-71	Xstr SMD BC857BW PNP SOT323
L112	059-15680-05	Ind SMD 0805cs 68nh 5%	Q530	000-10085-71	Xstr SMD BC857BW PNP SOT323
L113	036-10000-00	Res M/F SMD 0805 0e 0.125w	Q531	000-10084-71	Xstr BC847BW NPN SOT323
L114	036-10000-00	Res M/F SMD 0805 0e 0.125w	Q532	000-10084-71	Xstr BC847BW NPN SOT323
L115	057-10081-06	Ind 1806 Blm41p750s Emi Supr	Q533	000-10085-71	Xstr SMD BC857BW PNP SOT323
L116	052-57421-40	Coil A/W SMD 4t/2.1mm .57mm	Q535	000-10085-71	Xstr SMD BC857BW PNP SOT323
L119	036-10000-00	Res M/F SMD 0805 0e 0.125w	R1	038-13470-00	Res 0603 470e 1/16w +-5%
L122	052-57418-20	Coil A/W SMD 2t/1.8mm .57mm	R10	038-13150-00	Res 0603 150e 1/16w +-5%
L123	059-16390-05	Ind SMD 0805cs 390nh 5%	R100	038-13150-00	Res 0603 150e 1/16w +-5%
L125	059-15470-00	Ind SMD 0603hs 47nh 5%	R101	038-12390-00	Res 0603 39e 1/16w +-5%
L126	052-57418-30	Coil A/W SMD 3t/1.8mm .57mm	R102	038-13150-00	Res 0603 150e 1/16w +-5%
L130	052-57323-30	Coil A/W SMD 3t/2.3mm .57mm	R103	038-12470-00	Res 0603 47e 1/16w +-5%
L131	052-57418-30	Coil A/W SMD 3t/1.8mm .57mm	R104	038-13470-00	Res 0603 470e 1/16w +-5%
L132	052-57320-30	Coil A/W SMD 3t/2mm .57mm	R105	038-13470-00	Res 0603 470e 1/16w +-5%
L202	057-11220-02	Ind 0603 Blm11a221 Emi Supr	R106	036-12270-00	Res M/F SMD 0805 27e 5%
L203	057-11220-02	Ind 0603 Blm11a221 Emi Supr	R110	038-11470-00	Res 0603 4e7 1/16w +-5%
L270	050-10000-40	Coil SMD DC/DC Convrt	R111	038-14470-00	Res 0603 4k7 1/16w +-5%
L301	057-00015-00	Ind Fxd 15nh +-5% 1206 Mur	R112	038-15100-00	Res 0603 10k 1/16w +-5%
L302	059-16120-05	Ind SMD 0805cs 120nh 5%	R113	038-13470-00	Res 0603 470e 1/16w +-5%
L306	057-00015-00	Ind Fxd 15nh +-5% 1206 Mur	R114	038-13470-00	Res 0603 470e 1/16w +-5%
L307	057-00015-00	Ind Fxd 15nh +-5% 1206 Mur	R115	038-11680-00	Res 0603 6E8 1/16W +-5%
L308	059-16560-10	Ind SMD 1008cs 560nh 5%	R118	038-15220-00	Res 0603 22k 1/16w +-5%
L316	059-16820-10	Ind SMD 1008cs 820nh 5%	R119	036-11330-00	Res M/F SMD 0805 3e3 5%
L318	059-16820-15	Ind SMD 1008cs 820nh 2%	R12	038-15470-10	Res 0603 47k 1/16w+-1%
L401	059-15220-00	Ind SMD 0603hs 22nh 5%	R120	038-12470-00	Res 0603 47e 1/16w +-5%
L402	059-15150-00	Ind SMD 0603cs 15nh 5%	R121	036-13470-00	Res M/F SMD 0805 470e 5%
L404	059-15560-00	Ind SMD 0603hs 56nh 5%	R122	036-11330-00	Res M/F SMD 0805 3e3 5%
L408	052-57420-50	Coil A/W SMD 5t/2.0mm .57mm	R123	038-17100-00	Res 0603 1m 1/16w +-5%
L410	059-16330-05	Ind SMD 0805cs 330nh 5%	R124	036-11330-00	Res M/F SMD 0805 3e3 5%
L412	059-16330-05	Ind SMD 0805cs 330nh 5%	R125	038-14330-00	Res 0603 3k3 1/16w +-5%
L414	059-16330-05	Ind SMD 0805cs 330nh 5%	R126	038-11470-00	Res 0603 4e7 1/16w +-5%
L416	059-16330-05	Ind SMD 0805cs 330nh 5%	R13	038-15470-10	Res 0603 47k 1/16w+-1%
L420	059-16330-05	Ind SMD 0805cs 330nh 5%	R130	038-15220-00	Res 0603 22k 1/16w +-5%
L422	052-57421-40	Coil A/W SMD 4t/2.1mm .57mm	R131	038-13100-00	Res 0603 100e 1/16w +-5%
L424	059-16330-05	Ind SMD 0805cs 330nh 5%	R132	038-16100-00	Res 0603 100k 1/16w +-5%
L426	059-15560-00	Ind SMD 0603hs 56nh 5%	R133	038-16100-00	Res 0603 100k 1/16w +-5%
M202	539-00010-58	Vctcxo 12.8MHz+-2.5ppm -30+70	R134	038-15270-20	Res 0603 27k +-0.5%
PA	319-01207-03	Shld Pa Can Earth Tag T/Orca	R135	038-16100-00	Res 0603 100k 1/16w +-5%
PA-EX	319-01209-00	Shld Exciter T/Orca	R136	038-15100-20	Res 0603 10k +-0.5%
PA-LPF	319-01210-00	Shld Low Pass Fltr T/Orca	R139	036-12100-00	Res M/F SMD 0805 10e 5%
PL1	240-10000-14	Conn SMD 12w Non Zif 1mm	R14	038-14470-00	Res 0603 4k7 1/16w +-5%
Q1	000-10084-71	Xstr BC847BW NPN SOT323	R140	036-12100-00	Res M/F SMD 0805 10e 5%
Q100	000-10951-00	Xstr SMD PBR951 NPN SOT23	R141	036-12100-00	Res M/F SMD 0805 10e 5%
Q101	000-10085-71	Xstr SMD BC857BW PNP SOT323	R142	038-15100-00	Res 0603 10k 1/16w +-5%
Q102	000-10084-71	Xstr BC847BW NPN SOT323	R143	038-16470-00	Res 0603 470k 1/16w +-5%
Q103	000-10550-31	Xstr PD55003-01 3w 12.5v Csp	R144	038-15100-00	Res 0603 10k 1/16w +-5%
Q104	000-10085-71	Xstr SMD BC857BW PNP SOT323	R145	038-15270-00	Res 0603 27k 1/16w +-5%
Q105	000-10085-71	Xstr SMD BC857BW PNP SOT323	R146	036-12470-00	Res M/F SMD 0805 47e 5%
Q106	000-10151-80	Xstr SMD MRF1518 Mos Nch	R15	038-14220-00	Res 0603 2k2 1/16w +-5%
Q110	000-10084-71	Xstr BC847BW NPN SOT323	R150	036-00100-04	Res 1210 0e1 5% 0.5w
Q111	000-10084-71	Xstr BC847BW NPN SOT323	R151	038-15100-00	Res 0603 10k 1/16w +-5%
Q2	000-10084-71	Xstr BC847BW NPN SOT323	R152	038-16470-00	Res 0603 470k 1/16w +-5%
Q205	000-10084-71	Xstr BC847BW NPN SOT323	R153	036-03220-07	Res 2010 220e 5% 0.5w
Q280	000-10085-71	Xstr SMD BC857BW PNP SOT323	R154	038-15100-00	Res 0603 10k 1/16w +-5%
Q281	000-10084-71	Xstr BC847BW NPN SOT323	R155	038-15100-20	Res 0603 10k +-0.5%
Q3	000-11472-20	Xstr BTA7K BE22K NPN Dgtl	R156	038-12100-00	Res 0603 10e 1/16w +-5%
Q301	000-10941-00	Xstr SMD PBR941 NPN SOT23	R16	038-12330-00	Res 0603 33e 1/16w +-5%
Q305	002-10080-00	IC UPA800T 2x 2sc5008 Xstr	R160	038-14470-00	Res 0603 4k7 1/16w +-5%
Q307	000-10084-71	Xstr BC847BW NPN SOT323	R161	038-15270-20	Res 0603 27k +-0.5%
Q309	000-10418-10	Xstr 2SC4181 N SOT323 Hi B	R162	038-16150-00	Res 0603 150k 1/16w +-5%
Q320	000-10084-71	Xstr BC847BW NPN SOT323	R163	038-15330-00	Res 0603 33k 1/16w +-5%
Q321	000-10084-71	Xstr BC847BW NPN SOT323	R167	038-14100-00	Res 0603 1k0 1/16w +-5%
Q4	000-10085-71	Xstr SMD BC857BW PNP SOT323	R169	038-15270-00	Res 0603 27k 1/16w +-5%
Q400	000-10941-00	Xstr SMD PBR941 NPN SOT23	R17	038-13180-00	Res 0603 180e 1/16w +-5%
Q402	000-10941-00	Xstr SMD PBR941 NPN SOT23	R171	038-13680-00	Res 0603 680e 1/16w +-5%
Q404	000-10085-71	Xstr SMD BC857BW PNP SOT323	R172	038-13680-00	Res 0603 680e 1/16w +-5%
Q406	000-10085-71	Xstr SMD BC857BW PNP SOT323	R173	038-13680-00	Res 0603 680e 1/16w +-5%
Q5	000-10085-71	Xstr SMD BC857BW PNP SOT323	R174	038-15150-00	Res 0603 15k 1/16w +-5%
Q502	000-10084-71	Xstr BC847BW NPN SOT323	R2	038-13470-00	Res 0603 470e 1/16w +-5%
Q503	000-10085-71	Xstr SMD BC857BW PNP SOT323	R20	038-14220-00	Res 0603 2k2 1/16w +-5%
Q504	000-10084-71	Xstr BC847BW NPN SOT323	R202	038-15270-20	Res 0603 27k +-0.5%
			R203	038-15470-10	Res 0603 47k 1/16w+-1%
			R204	038-14100-00	Res 0603 1k0 1/16w +-5%
			R205	038-14100-00	Res 0603 1k0 1/16w +-5%
			R219	038-14100-00	Res 0603 1k0 1/16w +-5%
			R220	038-15120-00	Res 0603 12k 1/16w +-5%

Parts List for the Tait Orca H Band PCB (400 to 470 MHz)

Ref	IPN	Description	Ref	IPN	Description
R221	038-12220-00	Res 0603 22e 1/16w +5%	R402	038-13220-00	Res 0603 220e 1/16w +5%
R223	038-12470-00	Res 0603 47e 1/16w +5%	R404	038-14220-00	Res 0603 2k2 1/16w +5%
R224	038-12470-00	Res 0603 47e 1/16w +5%	R406	038-12330-00	Res 0603 33e 1/16w +5%
R225	038-12220-00	Res 0603 22e 1/16w +5%	R408	038-13330-00	Res 0603 330e 1/16w +5%
R227	038-10000-00	Res 0603 Zero Ohm 1/16w +5%	R410	038-14470-00	Res 0603 4k7 1/16w +5%
R228	038-14100-00	Res 0603 1k0 1/16w +5%	R412	038-12220-00	Res 0603 22e 1/16w +5%
R229	038-15180-00	Res 0603 18k 1/16w	R416	038-12220-00	Res 0603 22e 1/16w +5%
R230	038-15270-00	Res 0603 27k 1/16w +5%	R418	038-12220-00	Res 0603 22e 1/16w +5%
R234	038-14330-00	Res 0603 3k3 1/16w +5%	R420	038-12220-00	Res 0603 22e 1/16w +5%
R236	038-14470-00	Res 0603 4k7 1/16w +5%	R422	038-13470-00	Res 0603 470e 1/16w +5%
R237	038-14220-00	Res 0603 2k2 1/16w +5%	R424	038-13470-00	Res 0603 470e 1/16w +5%
R238	038-16470-00	Res 0603 470k 1/16w +5%	R426	038-12220-00	Res 0603 22e 1/16w +5%
R240	038-12470-00	Res 0603 47e 1/16w +5%	R428	038-12220-00	Res 0603 22e 1/16w +5%
R242	038-15150-00	Res 0603 15k 1/16w +5%	R430	038-13330-00	Res 0603 330e 1/16w +5%
R245	038-14220-00	Res 0603 2k2 1/16w +5%	R434	038-12470-00	Res 0603 47e 1/16w +5%
R246	038-14150-00	Res 0603 1k5 1/16w +5%	R436	038-14220-00	Res 0603 2k2 1/16w +5%
R270	038-12220-00	Res 0603 22e 1/16w +5%	R438	038-14470-00	Res 0603 4k7 1/16w +5%
R281	038-12220-00	Res 0603 22e 1/16w +5%	R440	038-12220-00	Res 0603 22e 1/16w +5%
R282	038-15470-10	Res 0603 47k 1/16w+1%	R442	038-12220-00	Res 0603 22e 1/16w +5%
R283	038-15270-00	Res 0603 27k 1/16w +5%	R444	038-14470-00	Res 0603 4k7 1/16w +5%
R284	038-13100-00	Res 0603 100e 1/16w +5%	R446	038-15220-00	Res 0603 22k 1/16w +5%
R285	038-13330-00	Res 0603 330e 1/16w +5%	R448	038-14470-00	Res 0603 4k7 1/16w +5%
R286	038-16105-10	Res 0603 105k 1/16w +1%	R450	038-13220-00	Res 0603 220e 1/16w +5%
R3	038-14100-00	Res 0603 1k0 1/16w +5%	R5	038-14220-00	Res 0603 2k2 1/16w +5%
R301	038-13470-00	Res 0603 470e 1/16w +5%	R501	038-14470-00	Res 0603 4k7 1/16w +5%
R302	038-14560-00	Res 0603 5k6 1/16w +5%	R502	038-16100-00	Res 0603 100k 1/16w +5%
R303	038-14180-00	Res 0603 1k8 1/16w	R503	038-15470-10	Res 0603 47k 1/16w+1%
R304	038-15100-00	Res 0603 10k 1/16w +5%	R504	038-15470-10	Res 0603 47k 1/16w+1%
R305	038-16100-00	Res 0603 100k 1/16w +5%	R505	038-15470-10	Res 0603 47k 1/16w+1%
R306	038-14470-00	Res 0603 4k7 1/16w +5%	R506	038-15470-10	Res 0603 47k 1/16w+1%
R308	038-15100-00	Res 0603 10k 1/16w +5%	R507	038-15470-10	Res 0603 47k 1/16w+1%
R309	038-16100-00	Res 0603 100k 1/16w +5%	R508	038-14470-00	Res 0603 4k7 1/16w +5%
R310	038-16100-00	Res 0603 100k 1/16w +5%	R510	038-15100-00	Res 0603 10k 1/16w +5%
R314	038-12470-00	Res 0603 47e 1/16w +5%	R511A	038-15270-20	Res 0603 27k +-0.5%
R315	038-13100-00	Res 0603 100e 1/16w +5%	R511B	045-15100-00	Res Ntc SMD 10k 5%
R316	038-13680-00	Res 0603 680e 1/16w +5%	R511C	038-15100-00	Res 0603 10k 1/16w +5%
R317	038-14180-00	Res 0603 1k8 1/16w	R511D	038-14470-00	Res 0603 4k7 1/16w +5%
R318	038-15330-00	Res 0603 33k 1/16w +5%	R512	038-15100-00	Res 0603 10k 1/16w +5%
R319	038-15100-00	Res 0603 10k 1/16w +5%	R513	038-15100-00	Res 0603 10k 1/16w +5%
R320	038-10000-00	Res 0603 Zero Ohm 1/16w +5%	R514	038-16100-00	Res 0603 100k 1/16w +5%
R321	038-14220-00	Res 0603 2k2 1/16w +5%	R515	038-15470-10	Res 0603 47k 1/16w+1%
R323	038-16100-00	Res 0603 100k 1/16w +5%	R516	038-16150-00	Res 0603 150k 1/16w +5%
R324	038-15100-00	Res 0603 10k 1/16w +5%	R517	038-15470-10	Res 0603 47k 1/16w+1%
R325	038-14100-00	Res 0603 1k0 1/16w +5%	R518	038-15270-00	Res 0603 27k 1/16w +5%
R326	038-13820-00	Res 0603 820e 1/16w +5%	R519	038-15220-00	Res 0603 22k 1/16w +5%
R327	038-14680-00	Res 0603 6k8 1/16w +5%	R520	038-16180-00	Res 0603 180k 1/16w +5%
R328	038-15270-00	Res 0603 27k 1/16w +5%	R521	038-15220-00	Res 0603 22k 1/16w +5%
R329	038-14220-00	Res 0603 2k2 1/16w +5%	R522	038-12220-00	Res 0603 22e 1/16w +5%
R330	038-14100-00	Res 0603 1k0 1/16w +5%	R523	038-10000-00	Res 0603 Zero Ohm 1/16w +5%
R331	038-13100-00	Res 0603 100e 1/16w +5%	R524	038-16100-00	Res 0603 100k 1/16w +5%
R333	038-16820-00	Res 0603 820k 1/16w +5%	R525	038-15470-10	Res 0603 47k 1/16w+1%
R334	038-15120-00	Res 0603 12k 1/16w +5%	R526	038-15100-00	Res 0603 10k 1/16w +5%
R335	038-15820-00	Res 0603 82k 1/16w +5%	R527	038-15470-10	Res 0603 47k 1/16w+1%
R336	038-15820-00	Res 0603 82k 1/16w +5%	R528	038-18100-00	Res 0603 10m 1/16w +5%
R337	038-10000-00	Res 0603 Zero Ohm 1/16w +5%	R529	038-15470-10	Res 0603 47k 1/16w+1%
R338	038-16150-00	Res 0603 150k 1/16w +5%	R530	038-14100-00	Res 0603 1k0 1/16w +5%
R339	038-17100-00	Res 0603 1m 1/16w +5%	R530A	038-15100-00	Res 0603 10k 1/16w +5%
R340	038-14270-00	Res 0603 2k7 1/16w +5%	R531	038-16100-00	Res 0603 100k 1/16w +5%
R341	038-16220-00	Res 0603 220k 1/16w +5%	R532	038-17100-00	Res 0603 1m 1/16w +5%
R342	038-16220-00	Res 0603 220k 1/16w +5%	R533	038-16105-10	Res 0603 105k 1/16w +1%
R344	038-16560-00	Res 0603 560k 1/16w +5%	R534	038-16100-00	Res 0603 100k 1/16w +5%
R345	038-12820-00	Res 0603 82e 1/16w +5%	R535	038-15100-20	Res 0603 10k +-0.5%
R346	038-14270-00	Res 0603 2k7 1/16w +5%	R536	038-15470-10	Res 0603 47k 1/16w+1%
R347	038-13820-00	Res 0603 820e 1/16w +5%	R537	038-15270-20	Res 0603 27k +-0.5%
R348	038-15150-00	Res 0603 15k 1/16w +5%	R538	038-16100-00	Res 0603 100k 1/16w +5%
R349	045-15100-00	Res Ntc SMD 10k 5%	R539	038-14220-00	Res 0603 2k2 1/16w +5%
R350	038-15150-00	Res 0603 15k 1/16w +5%	R540	038-14220-00	Res 0603 2k2 1/16w +5%
R351	038-16100-00	Res 0603 100k 1/16w +5%	R541	038-15390-00	Res 0603 39k 1/16w +5%
R352	038-10000-00	Res 0603 Zero Ohm 1/16w +5%	R542	038-15470-10	Res 0603 47k 1/16w+1%
R353	038-15100-00	Res 0603 10k 1/16w +5%	R543	038-15220-00	Res 0603 22k 1/16w +5%
R354	038-15150-00	Res 0603 15k 1/16w +5%	R544	038-15470-10	Res 0603 47k 1/16w+1%
R355	038-15470-10	Res 0603 47k 1/16w+1%	R545	038-16100-00	Res 0603 100k 1/16w +5%
R356	038-14470-00	Res 0603 4k7 1/16w +5%	R546	038-14100-00	Res 0603 1k0 1/16w +5%
R358	038-14220-00	Res 0603 2k2 1/16w +5%	R547	038-15470-10	Res 0603 47k 1/16w+1%
R365	038-13100-00	Res 0603 100e 1/16w +5%	R548	038-14220-00	Res 0603 2k2 1/16w +5%
R370	038-16680-00	Res 0603 680k 1/16w +5%	R549	038-10000-00	Res 0603 Zero Ohm 1/16w +5%
R371	038-14100-00	Res 0603 1k0 1/16w +5%	R550	038-14270-00	Res 0603 2k7 1/16w +5%
R372	038-16150-00	Res 0603 150k 1/16w +5%	R552	038-15470-10	Res 0603 47k 1/16w+1%
R373	038-15100-00	Res 0603 10k 1/16w +5%	R554	038-15470-10	Res 0603 47k 1/16w+1%
R380	038-15100-00	Res 0603 10k 1/16w +5%	R556	038-15470-10	Res 0603 47k 1/16w+1%
R381	038-15100-00	Res 0603 10k 1/16w +5%	R558	038-15470-10	Res 0603 47k 1/16w+1%
R390	038-16330-00	Res 0603 330k 1/16w +5%	R560	038-15470-10	Res 0603 47k 1/16w+1%
R391	038-15680-00	Res 0603 68k 1/16w +5%	R561	038-15470-10	Res 0603 47k 1/16w+1%
R392	045-15100-00	Res Ntc SMD 10k 5%	R562	038-15470-10	Res 0603 47k 1/16w+1%
R393	038-16100-00	Res 0603 100k 1/16w +5%	R564	038-15470-10	Res 0603 47k 1/16w+1%
R394	038-15100-00	Res 0603 10k 1/16w +5%	R565A	038-10000-00	Res 0603 Zero Ohm 1/16w +5%
R399	038-15100-00	Res 0603 10k 1/16w +5%	R565B	038-10000-00	Res 0603 Zero Ohm 1/16w +5%
R4	038-14100-00	Res 0603 1k0 1/16w +5%	R565D	038-10000-00	Res 0603 Zero Ohm 1/16w +5%

Parts List for the Tait Orca H Band PCB (400 to 470 MHz)

Ref	IPN	Description	Ref	IPN	Description
R566	038-14470-00	Res 0603 4k7 1/16w +5%	SWITCH	240-10100-01	Conn SMD Sw Micro Coax
R568	038-14470-00	Res 0603 4k7 1/16w +5%			
R570	038-15100-00	Res 0603 10k 1/16w +5%	SYNTH	319-01208-02	Shld Synth/lf T/Orca
R571	038-16680-00	Res 0603 680k 1/16w +-5%			
R572	038-10000-00	Res 0603 Zero Ohm 1/16w +-5%	VCOBOT	319-01206-01	Shld Bttm Slide VCO T/Orca
R573	038-14100-00	Res 0603 1k0 1/16w +5%	VCOTOP	319-01205-00	Shld Top Slide VCO T/Orca
R574	038-17560-00	Res 0603 5m6 1/16w +5%			
R575	038-11220-00	Res 0603 2e2 1/16w +5%	XF301	276-10000-12	Filtr Xtal 45.1m 12k B/W
R576	038-15100-20	Res 0603 10k +-0.5%	XF302	276-10000-13	Filtr Xtal 45.1m 15k B/W
R577	038-14680-00	Res 0603 6k8 1/16w +5%	XF303	276-10000-05	Filtr Cer SMD 455k 10k B/W
R578	038-15100-20	Res 0603 10k +-0.5%	XF304	276-10000-05	Filtr Cer SMD 455k 10k B/W
R579	038-14820-00	Res 0603 8k2 1/16w +5%	XL301	274-10016-00	Xtal SMD 44.645MHz Smx-1s Te22
R580	038-14100-00	Res 0603 1k0 1/16w +5%	XL501	274-10011-00	Xtal 16.128MHz +20ppm Tqy-1002
R581	038-14470-00	Res 0603 4k7 1/16w +5%			
R582	038-15180-00	Res 0603 18k 1/16w		220-01603-10	Pcb T/Orca 400-470m
R583	038-14680-00	Res 0603 6k8 1/16w +5%		FHW-0305	DSP V3.21 & New Synth H/W
R585	038-16100-00	Res 0603 100k 1/16w +-5%		FPG-OP-H2610	TOP Prog Test Spec
R586	038-15680-00	Res 0603 68k 1/16w +5%		FRF-OP61CNV2	TOP5020 Radio F/W V2.06
R587	038-17100-00	Res 0603 1m 1/16w +-5%		FSQ-OPH26103	TOP Squirt File
R588	038-15560-00	Res 0603 56k 1/16w +5%			
R589	038-14470-00	Res 0603 4k7 1/16w +5%			
R590	038-13470-00	Res 0603 470e 1/16w +-5%			
R591	038-15560-00	Res 0603 56k 1/16w +5%			
R6	038-12100-00	Res 0603 10e 1/16w +5%			
R601	038-15270-00	Res 0603 27k 1/16w +5%			
R602	038-14150-00	Res 0603 1k5 1/16w +5%			
R603	038-17100-00	Res 0603 1m 1/16w +-5%			
R604	038-15330-00	Res 0603 33k 1/16w +5%			
R606	038-15470-10	Res 0603 47k 1/16w+-1%			
R608	038-14330-00	Res 0603 3k3 1/16w +5%			
R610	038-14150-00	Res 0603 1k5 1/16w +5%			
R614	038-15470-10	Res 0603 47k 1/16w+-1%			
R615	038-15470-10	Res 0603 47k 1/16w+-1%			
R616	038-15270-00	Res 0603 27k 1/16w +5%			
R617	038-15220-00	Res 0603 22k 1/16w +5%			
R618	038-15100-00	Res 0603 10k 1/16w +5%			
R620	038-13100-00	Res 0603 100e 1/16w +-5%			
R630	038-16120-00	Res 0603 120k 1/16w +-5%			
R632	038-15120-00	Res 0603 12k 1/16w +5%			
R632A	038-17221-10	Res 0603 2m21 16w +-1%			
R633	038-16330-00	Res 0603 330k 1/16w +-5%			
R634	038-14470-00	Res 0603 4k7 1/16w +5%			
R635	038-15470-10	Res 0603 47k 1/16w+-1%			
R636	038-15220-00	Res 0603 22k 1/16w +5%			
R639	038-15470-10	Res 0603 47k 1/16w+-1%			
R640	038-16100-00	Res 0603 100k 1/16w +-5%			
R641	038-15270-00	Res 0603 27k 1/16w +5%			
R642	038-15470-10	Res 0603 47k 1/16w+-1%			
R643	038-15470-10	Res 0603 47k 1/16w+-1%			
R644	038-15220-00	Res 0603 22k 1/16w +5%			
R646	038-15100-00	Res 0603 10k 1/16w +5%			
R647	038-16100-00	Res 0603 100k 1/16w +-5%			
R648	038-15470-10	Res 0603 47k 1/16w+-1%			
R649	038-14470-00	Res 0603 4k7 1/16w +5%			
R650	038-14470-00	Res 0603 4k7 1/16w +5%			
R653	038-15470-10	Res 0603 47k 1/16w+-1%			
R654	038-16100-00	Res 0603 100k 1/16w +-5%			
R655	038-15470-10	Res 0603 47k 1/16w+-1%			
R656	038-14220-00	Res 0603 2k2 1/16w +5%			
R657	038-16180-00	Res 0603 180k 1/16w +-5%			
R658	038-15470-10	Res 0603 47k 1/16w+-1%			
R672	038-17100-00	Res 0603 1m 1/16w +-5%			
R674	038-17100-00	Res 0603 1m 1/16w +5%			
R676	038-17100-00	Res 0603 1m 1/16w +5%			
R678	038-16220-00	Res 0603 220k 1/16w +-5%			
R679	038-15100-00	Res 0603 10k 1/16w +5%			
R685	038-14100-00	Res 0603 1k0 1/16w +5%			
R685A	038-15470-10	Res 0603 47k 1/16w+-1%			
R686	038-14100-00	Res 0603 1k0 1/16w +5%			
R686A	038-15470-10	Res 0603 47k 1/16w+-1%			
R687	038-14100-00	Res 0603 1k0 1/16w +5%			
R688	038-17100-00	Res 0603 1m 1/16w +5%			
R689	038-13470-00	Res 0603 470e 1/16w +-5%			
R690	038-15100-00	Res 0603 10k 1/16w +5%			
R691	038-14100-00	Res 0603 1k0 1/16w +5%			
R692	038-15470-10	Res 0603 47k 1/16w+-1%			
R693	038-15470-10	Res 0603 47k 1/16w+-1%			
R694	038-15470-10	Res 0603 47k 1/16w+-1%			
R695	038-15470-10	Res 0603 47k 1/16w+-1%			
R7	038-12100-00	Res 0603 10e 1/16w +5%			
R8	038-13330-00	Res 0603 330e 1/16w +-5%			
R9	038-13470-00	Res 0603 470e 1/16w +5%			
RX	319-01213-01	Shld Rx T/Orca			
RX-FE	319-01215-01	Shld Frt End T/Orca			
RX-IF	319-01208-02	Shld Synth/lf T/Orca			
RXDEM	319-01211-00	Shld Dmodl T/Orca			