



ISSUE 2
 REDRAWN
 ITEM 3, CABLE,
 DELETED
 ITEMS RENUMBERED
 C/R 24500
 CM 12-02-96

NOTES:

8570 - DETAIL A

1. REMOVE 4 SCREWS SECURING CONSOLE TOP TO CHASSIS. DISCONNECT WIRING FROM CONNECTORS P1 AND P7 ON AUDIO PROCESSING PCB, P3 ON MICROCONTROLLER & DISPLAY PCB AND INTERCONNECTING EARTHING WIRE ENABLING TOP COVER TO BE SEPARATED FROM CHASSIS
2. IF CONVERTING FROM AN EXISTING 4W CONFIGURATION TO A 2W CONFIGURATION, REMOVE 4 SCREWS SECURING 4 WIRE INTERFACE PCB ASSEMBLY TO CHASSIS, DISCONNECT LOOM ON P9 OF AUDIO PROCESSING PCB ASSEMBLY AND WITHDRAW UNIT. REMOVE LOOM CONNECTOR FROM LINE POSITION OF REAR PANEL
3. FIT TYPE 8807 LINE ISOLATION UNIT 08-03816-001 TO CHASSIS WITH 2 SCREWS
4. FIT CONNECTOR TO P8 ON AUDIO PROCESSING PCB ASSEMBLY
5. REPLACE CABLES FROM MICROCONTROLLER & DISPLAY PCB. SECURE CONSOLE TOP TO CHASSIS WITH 4 SCREWS

8571 - DETAIL B

1. REMOVE 4 SCREWS SECURING TOP AND BOTTOM COVERS ON 8571 REMOTE CONTROL INTERFACE AND REMOVE COVERS
2. IF CONVERTING FROM AN EXISTING 4W CONFIGURATION TO A 2W CONFIGURATION, REMOVE 4 SCREWS SECURING 4 WIRE INTERFACE PCB ASSEMBLY TO CHASSIS ON APPROPRIATE LINE POSITION, DISCONNECT LOOM FROM RCI BACKPLANE AND WITHDRAW UNIT. REMOVE LOOM CONNECTOR FROM LINE X POSITION OF REAR PANEL (WHERE X IS 1 - 4)
3. FIT TYPE 8807 LINE ISOLATION UNIT 08-03816-001 TO CHASSIS WITH 2 SCREWS
4. FIT CONNECTOR TO LINE X POSITION ON RCI BACKPLANE CORRESPONDING TO LINE BEING FITTED
5. ENSURE LINE DISABLE LINK/S ARE IN PLACE ON BACKPLANE PCB CORRESPONDING TO NUMBER OF LINES FITTED, IN ACCORDANCE WITH 8571 LINE DISABLE LINK TABLES IN 8570/71 OPERATORS AND INSTALLATION HANDBOOK
6. FIT TOP AND BOTTOM COVERS TO 8571 REMOTE CONTROL INTERFACE AND REPLACE SCREWS

PARTS LIST

ITEM	PART No.	DESCRIPTION	QTY
-	15-10372-001	FITTING INSTRUCTIONS	
1	08-03816-001	LINE ISOLATION UNIT SINGLE CH	1
2	08-04146-001	CABLE, 6 WAY	1
3	31-23012-582	SCREW, M3x12	2
4	60-00063-501	SOCKET, 6 WAY MODULAR WALL MOUNT	1

REMOVE ALL BURRS & SHARP EDGES

	DRN	APJ	SCALE 1:1	© CODAN PTY LTD, A.C.N. 007 590 605 1995 TITLE OPTION 2W FITTING INSTRUCTIONS 8570/8571
	CHKD	AMJ	DATE 23-09-91	
	APPD	NJA	12-11-91	
	TOLERANCES UNLESS OTHERWISE STATED 2 PLACES DEC. ±0.25 1 PLACE DEC. ±0.5 0 PLACE DEC. ±1 ANGULAR ±2			
MATERIAL		FINISH		DRAWING/DOC NO. 15-10372-001
ISS AA			SHT. 1 OF 1	

FILE No.
 15\10372_2.DWG