

## MFJ-226 Windows Firmware Update Program

This program is a Windows based program that uses a Graphical User Interface instead of the older DOS based program originally issued.

This program does not have the COM port limitations that the older program had.

There are two versions of the Updater. One for Windows XP and the other for Windows Vista, 7, 8, and 10. This is a new addition as of 12-2-15. Older versions of the Updater will not work with Windows XP.

### Installing the program

1. Download the "MFJ-226 Update GUI\_20151126 W XP, 7, 8, 10.zip"
2. Extract the zip file to a convenient location that you can find easily.
3. Execute SETUP.EXE that is in the extracted folder for the proper version of Windows.
  - a. For Windows 7 and up accept the .NET 4.5 install by clicking on the left box with the (A) in it if this program is not already installed.
  - b. Answer YES to allow changes to the computer if requested.
  - c. Answer Install in the next box.
4. The update box should launch after the install.

The program will install and will show up in the ALL PROGRAMS or ALL APPS list in the folder TIMES TECHNOLOGY COMPANY as UPDATE TOOL. See your Windows version instructions as to where that list may be.

### Updating the firmware

1. Download the latest update and save in a convenient location. If it is in a zip file then extract it to a convenient location.
2. Connect the USB cable to the computer and the MFJ-226 and turn on the MFJ-226. Windows should find the drivers and install the MFJ-226.
  - a. The Updater program if running will show the COM port once it has installed.
  - b. Turn off the MFJ-226
3. Put the MFJ-226 into Firmware Update mode by holding the function key (lower left with the gear icon) in and press the power button. It will display "Firmware Update".
4. Launch the Update Tool if it is not already running. It should list the device and the port it is connected to. Example "Device Connected to COM3"
5. Open the file by clicking on the button then browsing to the new firmware update file which ends in .ENC
6. Click on the update button and the update should start.
7. Once finished turn off the MFJ-226 and click on the quit button to close the program.